



TS-231P3-4G

CPU	AnnapurnaLabs, an Amazon company Alpine AL314, 4-core, 1.7GHz
CPU Architecture	32-bit ARM
Floating Point Unit	Yes
Encryption Engine	Yes
System Memory	4GB SODIMM DDR3
Maximum Memory	8GB DDR3
Memory Slot	1 x SODIMM DDR3
Flash Memory	512 MB (Dual boot OS protection)
Drive Bay	2 x 3.5-inch SATA 6Gb/s, 3Gb/s
Drive Compatibility	3.5-inch bays: 3.5-inch SATA hard disk drives 2.5-inch SATA hard disk drives 2.5-inch SATA solid state drives
	Ver
Hot-swappable	Yes
Hot-swappable SSD Cache Acceleration Support	Yes
SSD Cache Acceleration	
SSD Cache Acceleration Support Gigabit Ethernet Port	Yes
SSD Cache Acceleration Support Gigabit Ethernet Port (RJ45) 2.5 Gigabit Ethernet Port	Yes 1
SSD Cache Acceleration SupportGigabit Ethernet Port (RJ45)2.5 Gigabit Ethernet Port (2.5G/1G/100M)	Yes 1 1(2.5G/1G/100M)
SSD Cache Acceleration SupportGigabit Ethernet Port (RJ45)2.5 Gigabit Ethernet Port (2.5G/1G/100M)Jumbo Frame	Yes 1 1(2.5G/1G/100M) Yes
SSD Cache Acceleration SupportGigabit Ethernet Port (RJ45)2.5 Gigabit Ethernet Port (2.5G/1G/100M)Jumbo FrameUSB 3.2 Gen 1 port	Yes 1 1(2.5G/1G/100M) Yes 3
SSD Cache Acceleration SupportGigabit Ethernet Port (RJ45)2.5 Gigabit Ethernet Port (2.5G/1G/100M)Jumbo FrameUSB 3.2 Gen 1 portForm Factor	Yes 1 1(2.5G/1G/100M) Yes 3 Tower
SSD Cache Acceleration SupportGigabit Ethernet Port (RJ45)2.5 Gigabit Ethernet Port (2.5G/1G/100M)Jumbo FrameUSB 3.2 Gen 1 portForm FactorLED Indicators	Yes11(2.5G/1G/100M)Yes3TowerPower, Status, LAN, USB, HDD1-2

Weight (Net)	1.46 kg
Weight (Gross)	2.46 kg
Operating Temperature	0 - 40 °C (32°F - 104°F)
Storage Temperature	-20 - 70°C (-4°F - 158°F)
Relative Humidity	5-95% RH non-condensing, wet bulb: 27°C (80.6°F)
Power Supply Unit	60W/65W adapter (12VDC), 100-240VAC
Power Consumption: HDD Sleep Mode	8.46 W
Power Consumption: Operating Mode, Typical	15.6 W
Fan	1 x70mm, 12VDC
System Warning	Buzzer
Kensington Security Slot	Yes
Max. Number of Concurrent Connections (CIFS) - with Max. Memory	400

Note: Use only QNAP memory modules to maintain system performance and stability. For NAS devices with more than one memory slot, use QNAP modules with identical specifications.

Warning: Using unsupported modules may degrade performance, cause errors, or prevent the operating system from starting. The terms HDMI, HDMI High-Definition Multimedia Interface, HDMI trade dress and the HDMI Logos are trademarks or registered trademarks of HDMI Licensing Administrator, Inc.

Product images are for illustrative purposes only and may differ from the actual product. Due to differences in monitors, colors of products may also appear different to those shown on the site.

Designs and specifications are subject to change without notice.