

GIGABYTE™

Redfish API Specification

for ASPEED AST2600

User Guide

Rev. 1.0

Copyright

© 2024 Giga Computing Technology CO., LTD. All rights reserved.

The trademarks mentioned in this manual are legally registered to their respective owners.

Disclaimer

Information in this manual is protected by copyright laws and is the property of Giga Computing. Changes to the specifications and features in this manual may be made by Giga Computing without prior notice. No part of this manual may be reproduced, copied, translated, transmitted, or published in any form or by any means without Giga Computing's prior written permission.

Documentation Classifications

In order to assist in the use of this product, Giga Computing provides the following types of documentation:

- User Manual: detailed information & steps about the installation, configuration and use of this product (e.g. motherboard, server barebones), covering hardware and BIOS.
- User Guide: detailed information about the installation & use of an add-on hardware or software component (e.g. BMC firmware, rail-kit) compatible with this product.
- Quick Installation Guide: a short guide with visual diagrams that you can reference easily for installation purposes of this product (e.g. motherboard, server barebones).

Please see the support section of the online product page to check the current availability of these documents.

For More Information

For related product specifications, the latest firmware and software, and other information please visit our website at <http://www.gigabyte.com/Enterprise>




For GIGABYTE distributors and resellers, additional sales & marketing materials are available from our reseller portal: <http://reseller.b2b.gigabyte.com>

For further technical assistance, please contact your GIGABYTE representative or visit <https://support.gigabyte.com/> to create a new support ticket

For any general sales or marketing enquiries, you may also message GIGABYTE server directly by email: server.grp@gigabyte.com

Conventions

The following conventions are used in this user's guide:

	NOTE! Pieces of additional information related to the current topic.
	CAUTION! Precautionary measures to avoid possible hardware or software problems.
	WARNING! Alerts to any damage that might result from doing or not doing specific actions.

Server Warnings and Cautions

Before installing a server, be sure that you understand the following warnings and cautions.



WARNING!

To reduce the risk of electric shock or damage to the equipment:

- Do not disable the power cord grounding plug. The grounding plug is an important safety feature.
- Plug the power cord into a grounded (earthed) electrical outlet that is easily accessible at all times.
- Unplug the power cord from the power supply to disconnect power to the equipment.
- Do not route the power cord where it can be walked on or pinched by items placed against it. Pay particular attention to the plug, electrical outlet, and the point where the cord extends from the server.



WARNING!

To reduce the risk of personal injury from hot surfaces, allow the drives and the internal system components to cool before touching them.



WARNING!

This server is equipped with high speed fans. Keep away from hazardous moving fan blades during servicing.



CAUTION!

- Do not operate the server for long periods with the access panel open or removed. Operating the server in this manner results in improper airflow and improper cooling that can lead to thermal damage.
- Danger of explosion if battery is incorrectly replaced.
- Replace battery with the same or equivalent type recommended by the manufacturer.
- Dispose of used batteries according to the manufacturer's instructions.



CAUTION!

Risk of explosion if battery is replaced incorrectly or with an incorrect type. Replace the battery only with the same or equivalent type recommended by the manufacturer. Dispose of used batteries according to the manufacturer's instructions.



Electrostatic Discharge (ESD)

CAUTION!

ESD CAN DAMAGE DRIVES, BOARDS, AND OTHER PARTS. WE RECOMMEND THAT YOU PERFORM ALL PROCEDURES AT AN ESD WORKSTATION. IF ONE IS NOT AVAILABLE, PROVIDE SOME ESD PROTECTION BY WEARING AN ANTI-STATIC WRIST STRAP ATTACHED TO CHASSIS GROUND -- ANY UNPAINTED METAL SURFACE -- ON YOUR SERVER WHEN HANDLING PARTS.

Always handle boards carefully, they can be extremely sensitive to ESD. Hold boards only by their edges without touching any components or connectors. After removing a board from its protective ESD bag or from the system, place the board component side up on a grounded, static free surface. Use a conductive foam pad if available but not the ESD bag. Do not slide the board over any surface.

System power on/off: To service components within the server, please ensure the power has been disconnected.

e.g. Remove the node from the server chassis (to disconnect power) or disconnect the power from the server chassis.

Make sure the system is removed from the rack before opening the chassis, adding, or removing any non hot-plug components.

Hazardous conditions, devices and cables: Hazardous electrical conditions may be present on power, telephone, and communication cables. Turn off the system chassis and disconnect the cables attached to the system before servicing the chassis. Otherwise, personal injury or equipment damage can result.

Electrostatic discharge (ESD) and ESD protection: ESD can damage drives, boards, and other parts. We recommend that you perform all procedures in this chapter only at an ESD workstation. If one is not available, provide some ESD protection by wearing an antistatic wrist strap attached to chassis ground (any unpainted metal surface on the server) when handling parts.

ESD and handling boards: Always handle boards carefully. They can be extremely sensitive to electrostatic discharge (ESD). Hold boards only by their edges. After removing a board from its protective wrapper or from the system, place the board component side up on a grounded, static free surface. Use a conductive foam pad if available but not the board wrapper. Do not slide board over any surface.

Installing or removing jumpers: A jumper is a small plastic encased conductor that slips over two jumper pins. Some jumpers have a small tab on top that can be gripped with fingertips or with a pair of fine needle nosed pliers. If the jumpers do not have such a tab, take care when using needle nosed pliers to remove or install a jumper; grip the narrow sides of the jumper with the pliers, never the wide sides. Gripping the wide sides can damage the contacts inside the jumper, causing intermittent problems with the function controlled by that jumper. Take care to grip with, but not squeeze, the pliers or other tool used to remove a jumper, or the pins on the board may bend or break.

Table of Contents

1. Introduction.....	10
2. Redfish Request Methods	11
2-1 HTTP GET (Read).....	11
2-2 HTTP POST (Create).....	11
2-3 HTTP PATCH (Partial Update).....	11
2-4 HTTP DELETE (Delete).....	11
3. Redfish API.....	12
4. Common Field to all Schemas	21
5. ServiceRoot.....	21
6. ODATA.....	22
7. \$metadata	22
8. AccountServicea	23
8-1 Account Collection	24
8-1-1 Accounts.....	24
8-2 PAM Configuration	25
8-3 Radius Authentication	25
8-3-1 AdvancedRADIUSSetting.....	25
8-4 Role Collection	26
8-4-1 Role.....	26
9. CertificateService	28
9-1 CertificateLocations.....	29
9-1-1 Certificate	30
10. Chassis Collection.....	31
10-1 Chassis	31
10-1-1 Power	32
10-1-2 LogServices (Support services after version 12.41.07).....	34
10-1-3 Sensor Collection	35
10-1-4 Thermal	37
10-1-5 NetworkAdapterCollection	39
10-1-6 PCIeDevice Collection.....	39
11. CompositionService	41
11-1 ResourceBlocks Collection	41

11-1-1	ResourceBlocks.....	41
11-2-1	ResourceZones	42
12.	AMI OEM Entities - Configuration	43
13.	EventService	44
13-1	Subscription Collection.....	45
13-1-1	Subscription.....	46
13-1-2	Subscription Test Event	46
14.	JsonSchemas Collection	47
14-1	JsonSchemas.....	47
15.	Manager Collection	48
15-1	Manager.....	48
15-1-1	EthernetInterfaces Collection	50
15-1-2	CertificateCollection.....	53
15-1-3	Factory Reset ActionInfo	53
15-1-4	HostInterfaces Collection.....	53
15-1-5	LogServices Collection	54
15-1-6	NetworkProtocol	57
15-1-7	Reset ActionInfo	57
15-1-8	SerialInterfaces Collection.....	58
15-1-9	VirtualMedia Collection.....	58
16.	InventoryDataMessage Registry File Collection.....	61
16-1	Message Registries.....	61
16-2	Message Registries File.....	61
17.	Session Service.....	62
17-1	Session Collection.....	62
17-1-1	Session.....	63
18.	System Collection.....	64
18-1	Capabilities.....	64
18-2	System	65
18-2-1	BIOS.....	66
18-2-2	BootOption Collection.....	68
18-2-3	EthernetInterfaces Collection	68
18-2-4	LogServices Collection	70
18-2-5	Memory Collection.....	71
18-2-6	MemoryDomains Collection.....	73
18-2-7	NetworkInterface Collection.....	73
18-2-8	Processor Collection.....	73
18-2-9	SimpleStorage Collection	74

18-2-10 Storage Collection	75
19. RedundancyTaskService	76
19-1 Task Collection	76
19-1-1 Task	76
20. TelemetryService	77
20-1 MetricReportLog Collection	77
20-1-1 MetricReportLog	78
20-2-1 MetricDefinitions	79
20-3-1 MetricReportDefinitions	80
20-4-1 MetricReports	81
20-5-1 Triggers	82
21. UpdateService	83
21-1 SimpleUpdateActionInfo	83
21-2 FirmwareInventory Collection	84
21-2-1 FirmwareInventory	84
22. Extension Redfish API	85
22-1 Chassis (Only for Grace)	85
22-1-1 Asembly	86
22-1-2 Capabilities	86
22-1-3 Controls Collection	86
22-1-4 LogServices Collection	87
22-1-5 PCIe Devices Collection	88
22-1-6 Sensor Collection	89
22-2 System (Only for Grace)	90
22-2-1 Memory	90
22-2-2 Processor	91
22-3 UpdateService (Only for Grace)	93
22-3-1 FirmwareInventory	93
22-3-2 SoftwareInventory	93

1. Introduction

The Redfish Scalable Platform Management API ("Redfish") is a management standard using a data model representation inside of a hypermedia RESTful interface. Because it is based on REST, Redfish is easier to use and implement than many other solutions. Since it is model oriented, it is capable of expressing the relationships between components in modern systems as well as the semantics of the services and components within them. It is also easily extensible. By using a hypermedia approach to REST, Redfish can express a large variety of systems from multiple vendors. By requiring JSON representation, a wide variety of resources can be created in a denormalized fashion not only to improve scalability, but the payload can be easily interpreted by most programming environments as well as being relatively intuitive for a human examining the data. The model is exposed in terms of an interoperable Redfish Schema, expressed in an OData Schema representation with translations to a JSON Schema representation, with the payload of the messages being expressed in a JSON following OData JSON conventions. The ability to externally host the Redfish Schema definition of the resources in a machine-readable format allows the meta data to be associated with the data without encumbering Redfish services with the meta data, thus enabling more advanced client scenarios as found in many data center and cloud environments.

2. Redfish Request Methods

The following HTTP methods are provided on our Redfish APIs.

2-1 HTTP GET (Read)

Use GET requests to retrieve resource representation/information only. For any given HTTP GET API, if resource is found on server then it must return HTTP response code 200 (OK) – along with response body which is JSON content. In case resource is NOT found on server then it must return HTTP response code 404 (NOT FOUND). Similarly, if it is determined that GET request itself is not correctly formed then server will return HTTP response code 400 (BAD REQUEST).

2-2 HTTP POST (Create)

Use POST APIs to create new subordinate resources, POST methods are used to create a new resource into the collection of resources. In this case, either HTTP response code 200 (OK) or 204 (No Content) is the appropriate

2-3 HTTP PATCH (Partial Update)

HTTP PATCH requests are **to make partial update on a resource**.

2-4 HTTP DELETE (Delete)

DELETE APIs are used to delete resources. A successful response of DELETE requests SHOULD be HTTP response code 200 (OK) if the response includes an entity describing the status, 202 (Accepted) if the action has been queued, or 204 (No Content) if the action has been performed but the response does not include an entity.

3. Redfish API

Resource API	Note
/redfish/v1	
/redfish/v1/odata	
/redfish/v1/\$metadata	
/redfish/v1/AccountService	
/redfish/v1/AccountService/Accounts	
/redfish/v1/AccountService/Accounts/{instance}	
/redfish/v1/AccountService/Accounts/{instance}	
/redfish/v1/AccountService/Configurations	
/redfish/v1/AccountService/ExternalAccountProviders/RADIUS	
/redfish/v1/AccountService/ExternalAccountProviders/RADIUS/Oem/Ami/AdvancedRADIUS-Setting	
/redfish/v1/AccountService/LDAP/Certificates	
/redfish/v1/AccountService/LDAP/Certificates/1	
/redfish/v1/AccountService/LDAP/Certificates/Oem/Ami/ClientCertificates	
/redfish/v1/AccountService/LDAP/Certificates/Oem/Ami/ClientCertificates/1	
/redfish/v1/AccountService/Roles	
/redfish/v1/AccountService/Roles/{instance}	
/redfish/v1/CertificateService	
/redfish/v1/CertificateService/Actions/CertificateService.GenerateCSR	
/redfish/v1/CertificateService/Actions/CertificateService.ReplaceCertificate	
/redfish/v1/CertificateService/CertificateLocations	
/redfish/v1/Chassis	
/redfish/v1/Chassis/{instance}	
/redfish/v1/Chassis/{instance}/Actions/Chassis.Reset	
/redfish/v1/Chassis/{instance}/Power	
/redfish/v1/Chassis/{instance}/LogServices	
/redfish/v1/Chassis/{instance}/LogServices/Logs/Entries	
/redfish/v1/Chassis/{instance}/LogServices/Logs/Entries/{instance}	
/redfish/v1/Chassis/{instance}/LogServices/Logs	
/redfish/v1/Chassis/{instance}/LogServices/Logs/Actions/LogService.ClearLog	
/redfish/v1/Chassis/{instance}/NetworkAdapters	

Resource API	Note
/redfish/v1/Chassis/{instance}/PCleDevices	
/redfish/v1/Chassis/{instance}/PCleDevices/{instance}	
/redfish/v1/Chassis/{instance}/PCleDevices/{instance}/PCleFunctions/{instance}	
/redfish/v1/Chassis/{instance}/Sensors	
/redfish/v1/Chassis/{instance}/Sensors/{instance}	
/redfish/v1/Chassis/{instance}/Sensors/Energy	
/redfish/v1/Chassis/{instance}/Sensors/Power	
/redfish/v1/Chassis/{instance}/Thermal	
/redfish/v1/Chassis/{instance}/Thermal/FanprofileService	
/redfish/v1/Chassis/{instance}/Thermal/FanprofileService/Fanprofile	
/redfish/v1/Chassis/{instance}/Thermal/FanprofileService/SupportPCIEDevice	
/redfish/v1/Oem/Ami/Configurations	
/redfish/v1/CompositionService	
/redfish/v1/CompositionService/ResourceBlocks	
/redfish/v1/CompositionService/ResourceBlocks/{instance}	
/redfish/v1/CompositionService/ResourceZones	
/redfish/v1/CompositionService/ResourceZones/{ instance }	
/redfish/v1/EventService	
/redfish/v1/EventService/Actions/EventService.SubmitTestEvent	
/redfish/v1/EventService/Subscriptions	
/redfish/v1/EventService/Subscriptions/{instance}	
/redfish/v1/EventService/SubmitTestEventActionInfo	
/redfish/v1/JsonSchemas	
/redfish/v1/JsonSchemas/{instance}	
/redfish/v1/Managers	
/redfish/v1/Managers/{instance}	

Resource API	Note
/redfish/v1/Managers/{instance}/Actions/Oem/AMIManager.RedfishDBReset	
redfish/v1/Managers/{instance}/EthernetInterfaces	
redfish/v1/Managers/{instance}/EthernetInterfaces/{instance}	
redfish/v1/Managers/{instance}/HostInterfaces	
redfish/v1/Managers/{instance}/HostInterfaces/{instance}	
redfish/v1/Managers/{instance}/HostInterfaces/{instance}/HostEthernetInterfaces	
/redfish/v1/Managers/{instance}/LogServices	
/redfish/v1/Managers/{instance}/LogServices/{instance}	
/redfish/v1/Managers/{instance}/LogServices/{instance}/Actions/LogServices.ClearLog	
/redfish/v1/Managers/{instance}/LogServices/{instance}/Entries	
/redfish/v1/Managers/{instance}/LogServices/{instance}/Entries/{instance}	
/redfish/v1/Managers/{instance}/NetworkProtocol	
/redfish/v1/Managers/{instance}/NetworkProtocol/HTTPS/Certificates	
/redfish/v1/Managers/{instance}/NetworkProtocol/HTTPS/Certificates/{instance}	
/redfish/v1/Managers/{instance}/Oem/RedfishDBResetActionInfo	
/redfish/v1/Managers/{instance}/ResetActionInfo	
/redfish/v1/Managers/{instance}/SerialInterfaces	
/redfish/v1/Managers/{instance}/SerialInterfaces/{instance}	
/redfish/v1/Managers/{instance}/VirtualMedia	
/redfish/v1/Managers/{instance}/VirtualMedia/{instance}	

Resource API	Note
/redfish/v1/Managers/{instance}/VirtualMedia/{instance}/Actions/VirtualMedia.InsertMedia	
/redfish/v1/Managers/{instance}/VirtualMedia/{instance}/Actions/VirtualMedia.EjectMedia	
/redfish/v1/Managers/{instance}/Actions/Oem/AMIVirtualMedia.ConfigureCDInstance	
/redfish/v1/Managers/{instance}/Actions/Oem/AMIVirtualMedia.EnableRMedia	
/redfish/v1/Registries	
/redfish/v1/Registries/{instance}	
/redfish/v1/Registries/{instance.json}	
/redfish/v1/SessionService	
/redfish/v1/SessionService/Sessions	
/redfish/v1/SessionService/Sessions/{instance}	
/redfish/v1/Systems	
/redfish/v1/Systems/Capabilities	
/redfish/v1/Systems/{instance}	
/redfish/v1/Systems/{instance}/Actions/ComputerSystem.Reset	
/redfish/v1/Systems/{instance}/Bios	
/redfish/v1/Systems/{instance}/Bios/Actions/Bios.ResetBios	
/redfish/v1/Systems/{instance}/Bios/Actions/Bios.ChangePassword	
/redfish/v1/Systems/{instance}/Bios/SD	
/redfish/v1/Systems/{instance}/BootOptions	
/redfish/v1/Systems/{instance}/BootOptions/{instance}	
/redfish/v1/Systems/{instance}/EthernetInterfaces	
/redfish/v1/Systems/{instance}/EthernetInterfaces/{instance}	

Resource API	Note
/redfish/v1/Systems/{instance}/EthernetInterfaces/{instance}/VLANS	
/redfish/v1/Systems/{instance}/EthernetInterfaces/{instance}/VLANS/{instance}	
/redfish/v1/Systems/{instance}/LogServices	
/redfish/v1/Systems/{instance}/LogServices/{instance}	
/redfish/v1/Systems/{instance}/LogServices/{instance}/Actions/LogService.ClearLog	
/redfish/v1/Systems/{instance}/LogServices/{instance}/Entries	
/redfish/v1/Systems/{instance}/LogServices/{instance}/Entries/{instance}	
/redfish/v1/Systems/{instance}/Memory	
/redfish/v1/Systems/{instance}/Memory/{instance}	
/redfish/v1/Systems/{instance}/MemoryDomains	
/redfish/v1/Systems/{instance}/NetworkInterfaces	
/redfish/v1/Systems/{instance}/NetworkInterfaces/{instance}	
/redfish/v1/Systems/{instance}/Processors	
/redfish/v1/Systems/{instance}/Processors/{instance}	
/redfish/v1/Systems/{instance}/SimpleStorage	
/redfish/v1/Systems/{instance}/SimpleStorage/{instance}	
/redfish/v1/Systems/{instance}/Storage	
/redfish/v1/Systems/{instance}/Storage /{instance}	
/redfish/v1/TaskService	
/redfish/v1/TaskService/Tasks	
/redfish/v1/TaskService/Tasks/{instance}	
/redfish/v1/TelemetryService	
/redfish/v1/TelemetryService/Actions/ TelemetryService.SubmitTestMetricReport	
/redfish/v1/TelemetryService/LogServices	
/redfish/v1/TelemetryService/LogService/Actions/LogService.ClearLog	

Resource API	Note
/redfish/v1/TelemetryService/LogServices	
/redfish/v1/TelemetryService/LogServices/Actions/LogService.ClearLog	
/redfish/v1/TelemetryService/LogServices/Entries	
/redfish/v1/TelemetryService/LogServices/Entries/{instance}	
/redfish/v1/TelemetryService/MetricDefinitions	
/redfish/v1/TelemetryService/MetricDefinitions/{instance}	
/redfish/v1/TelemetryService/MetricReportDefinitions	
/redfish/v1/TelemetryService/MetricReportDefinitions/{instance}	
/redfish/v1/TelemetryService/MetricReports	
/redfish/v1/TelemetryService/MetricReports/{instance}	
/redfish/v1/TelemetryService/Triggers	
/redfish/v1/TelemetryService/Triggers/{instance}	
/redfish/v1/UpdateService	
/redfish/v1/UpdateService/Actions/SimpleUpdate	
/redfish/v1/UpdateService/FirmwareInventory	
/redfish/v1/UpdateService/FirmwareInventory/{instance}	
/redfish/v1/UpdateService/SimpleUpdateActionInfo	

Resource API	Note
/redfish/v1/Chassis/Baseboard_{instanceId}	Only for Grace
/redfish/v1/Chassis/Baseboard_{instanceId}/Assembly	Only for Grace
/redfish/v1/Chassis/Baseboard_{instanceId}/Oem/Nvidia/Capabilities	Only for Grace
/redfish/v1/Chassis/Baseboard_{instanceId}/Sensors	Only for Grace
/redfish/v1/Chassis/Baseboard_{instanceId}/Sensors/{instance}	Only for Grace
/redfish/v1/Chassis/CPU_{instanceId}	Only for Grace
/redfish/v1/Chassis/CPU_{instanceId}/Sensors	Only for Grace
/redfish/v1/Chassis/CPU_{instanceId}/Sensors/{instance}	Only for Grace
/redfish/v1/Chassis/ERoT_CPU_{instanceId}	Only for Grace
/redfish/v1/Chassis/ERoT_CPU_{instanceId}/LogServices	Only for Grace
/redfish/v1/Chassis/ERoT_CPU_{instanceId}/LogServices/DebugTokenService	Only for Grace
/redfish/v1/Chassis/ERoT_CPU_{instanceId}/LogServices/DebugTokenService/Actions/LogService.CollectDiagnosticData	Only for Grace
/redfish/v1/Chassis/ERoT_CPU_{instanceId}/LogServices/DebugTokenService/Entries	Only for Grace
/redfish/v1/Chassis/ERoT_CPU_{instanceId}/Sensors	Only for Grace
/redfish/v1/Chassis/ERoT_CPU_{instanceId}/Sensors/{instance}	Only for Grace
/redfish/v1/Chassis/ERoT_GPU_{instanceId}	Only for Grace
/redfish/v1/Chassis/ERoT_GPU_{instanceId}/LogServices	Only for Grace
/redfish/v1/Chassis/ERoT_GPU_{instanceId}/LogServices/DebugTokenService	Only for Grace
/redfish/v1/Chassis/ERoT_GPU_{instanceId}/LogServices/DebugTokenService/Actions/LogService.CollectDiagnosticData	Only for Grace
/redfish/v1/Chassis/ERoT_GPU_{instanceId}/LogServices/DebugTokenService/Entries	Only for Grace

Resource API	Note
/redfish/v1/Chassis/ERoT_GPU_{instanceId}/LogServices/DebugTokenService/Entries/{instance}	Only for Grace
/redfish/v1/Chassis/ERoT_GPU_{instanceId}/Sensors	Only for Grace
/redfish/v1/Chassis/ERoT_GPU_{instanceId}/Sensors/{instance}	Only for Grace
/redfish/v1/Chassis/FPGA_{instanceId}	Only for Grace
/redfish/v1/Chassis/FPGA_{instanceId}/Oem/Nvidia/Capabilities	Only for Grace
/redfish/v1/Chassis/FPGA_{instanceId}/Sensors	Only for Grace
/redfish/v1/Chassis/FPGA_{instanceId}/Sensors/{instance}	Only for Grace
/redfish/v1/Chassis/GPU_{instanceId}	Only for Grace
/redfish/v1/Chassis/GPU_{instanceId}/Assembly	Only for Grace
/redfish/v1/Chassis/GPU_{instanceId}/Oem/Nvidia/Capabilities	Only for Grace
/redfish/v1/Chassis/GPU_{instanceId}/PCleDevices	Only for Grace
/redfish/v1/Chassis/GPU_{instanceId}/PCleDevices/{instance}	Only for Grace
/redfish/v1/Chassis/GPU_{instanceId}/Sensors	Only for Grace
/redfish/v1/Chassis/GPU_{instanceId}/Sensors/{instance}	Only for Grace
/redfish/v1/Chassis/ProcessorModule_{instanceId}	Only for Grace
/redfish/v1/Chassis/ProcessorModule_{instanceId}/Controls	Only for Grace
/redfish/v1/Chassis/ProcessorModule_{instanceId}/Controls/{instance}	Only for Grace
/redfish/v1/Chassis/ProcessorModule_{instanceId}/Sensors	Only for Grace
/redfish/v1/Chassis/ProcessorModule_{instanceId}/Sensors/{instance}	Only for Grace
/redfish/v1/Systems/{instance}/Memory/GPU_{instanceId}_DRAM_{instanceId}	Only for Grace
/redfish/v1/Systems/{instance}/Memory/GPU_{instanceId}_DRAM_{instanceId}/EnvironmentMetrics	Only for Grace

Resource API	Note
/redfish/v1/Systems/{instance}/Memory/GPU_{instanceId}_DRAM_{instanceId}/MemoryMetrics	Only for Grace
/redfish/v1/Systems/{instance}/Processors/FPGA_{instanceId}	Only for Grace
/redfish/v1/Systems/{instance}/Processors/FPGA_{instanceId}/Ports	Only for Grace
/redfish/v1/Systems/{instance}/Processors/FPGA_{instanceId}/Ports/{instance}	Only for Grace
/redfish/v1/Systems/{instance}/Processors/FPGA_{instanceId}/Ports/{instance}/Metrics	Only for Grace
/redfish/v1/Systems/{instance}/Processors/GPU_{instanceId}	Only for Grace
/redfish/v1/Systems/{instance}/Processors/GPU_{instanceId}/EnvironmentMetrics	Only for Grace
/redfish/v1/Systems/{instance}/Processors/GPU_{instanceId}/MemorySummary/MemoryMetrics	Only for Grace
/redfish/v1/Systems/{instance}/Processors/GPU_{instanceId}/ProcessorMetrics	Only for Grace
/redfish/v1/UpdateService/FirmwareInventory /CPU_{instanceId}	Only for Grace
/redfish/v1/UpdateService/FirmwareInventory /ERoT_CPU_{instanceId}	Only for Grace
/redfish/v1/UpdateService/FirmwareInventory /ERoT_GPU_{instanceId}	Only for Grace
/redfish/v1/UpdateService/FirmwareInventory /FPGA_{instanceId}	Only for Grace
/redfish/v1/UpdateService/FirmwareInventory /FW_GPU_{instanceId}	Only for Grace
/redfish/v1/UpdateService/FirmwareInventory /InfoROM_GPU_{instanceId}	Only for Grace
/redfish/v1/UpdateService/SoftwareInventory	Only for Grace
/redfish/v1/UpdateService/SoftwareInventory/Driver_GPU_{instanceId}	Only for Grace

4. Common Field to all Schemas

- @odata.context
- @odata.id
- @odata.type - @odata.etag
- Id
- Name

5. ServiceRoot

[GET] /redfish/v1

- Oem
 - Ami
 - Configurations
 - RtpVersion
- Id
- Name
- Description
- RedfishVersion
- Systems
- Chassis
 - Managers
 - Tasks
 - AccountService
 - EventService
 - SessionService
 - Registries
 - JsonSchemas
 - UpdateService
 - CompositionService
 - TelemetryService
 - Links
 - Sessions
- JobService
- Product
- ProtocolFeaturesSupported
- ExcerptQuery
 - ExpandQuery
 - ExpandAll
 - Levels
 - Links
 - MaxLevels
 - NoLinks
- FilterQuery
- OnlyMemberQuery
- SelectQuery

- *UUID*
- *Vendor*
- *CertificateService*
- *Oem*

6. ODATA

[GET] /redfish/v1/odata

7. \$metadata

[GET] /redfish/v1/\$metadata

8. AccountServicea

[GET] /redfish/v1/AccountService

[PATCH] /redfish/v1/AccountService

- AccountLockoutCounterResetAfter
- AccountLockoutDuration
- AccountLockoutThreshold
- Accounts
- AuthFailureLoggingThreshold
- Description
- Id
- MaxPasswordLength
- MinPasswordLength
- Name
- Oem
 - Ami
 - Configuration
- Roles
- ServiceEnabled
- Status
 - Health
 - State
- PrivilegeMap
- ActiveDirectory
- Authentication
 - AuthenticationType
 - Username
 - Password
- RemoteRoleMapping
- ServiceEnabled
- AccountLockoutCounterResetEnabled- AdditionalExternalAccountProviders
- LDAP
 - Authentication
 - AuthenticationType
 - Username
 - Password
 - LDAPService
 - SearchSettings
 - GroupNameAttribute
 - GroupsAttribute
 - UsernameAttribute
- RemoteRoleMapping
- ServiceEnabled

8-1 Account Collection

[GET] /redfish/v1/AccountService/Accounts

[POST] /redfish/v1/AccountService/Accounts

- **Description**
- **Members@odata.count**
- **Members**
- **Name- Oem**

POST

Request:

```
POST https://{{ip}}/redfish/v1/AccountService/Accounts
Content-Type: application/json
```

Example POST Request Body:

```
{ "Name":
  "TestUser Account",
  "Description": "Test User Account",
  "Enabled": true,
  "Password": "superuser",
  "UserName": "user_account",
  "RoleId": "Operator",
  "Locked": false,
  "PasswordChangeRequired": false
}
```

8-1-1 Accounts

[GET] /redfish/v1/AccountService/Accounts/{instance}

[PATCH] /redfish/v1/AccountService/Accounts/{instance}

[DELETE] /redfish/v1/AccountService/Accounts/{instance}

Description

- **Enabled**
- **Id**
- **Links**
- **Role**
- **Locked**
- **Name**
- **RoleId**
- **UserName**
- **Password**
- **PasswordChangeRequired**
- **Oem**
- **Actions**

- **Certificates**
- **AccountTypes**
- **Certificates**
- **AccountTypes**
- **SNMP**
 - **AuthenticationProtocol**
 - **EncryptionProtocol**

8-2 PAM Configuration

[GET] /redfish/v1/AccountService/Configurations

[PATCH] /redfish/v1/AccountService/Configurations

- **Id**
- **Name**
- **PAMEnabled**
- **PAMOrder**

8-3 Radius Authentication

[GET] /redfish/v1/AccountService/ExternalAccountProviders/RADIUS

[PATCH] /redfish/v1/AccountService/ExternalAccountProviders/RADIUS

- **ServicePort**
- **ServiceEnabled**
- **ExtendedPrivilege**
- **ServiceAddress**
- **Secret**
- **ExtendedPrivilege**
 - **KVMAccess**
 - **VMediaAccess**
- **AdvancedRADIUSSetting**
- **Timeout**
- **AccountProviderTypes**
- **Oem**

8-3-1 AdvancedRADIUSSetting

[GET] /redfish/v1/AccountService/ExternalAccountProviders/RADIUS/Oem/Ami/AdvancedRADIUSSetting

[PATCH] /redfish/v1/AccountService/ExternalAccountProviders/RADIUS/Oem/Ami/AdvancedRADIUSSetting

- **RADIUSAuthorization**

8-4 Role Collection

[GET] /redfish/v1/AccountService/Roles

[POST] /redfish/v1/AccountService/Roles

- **Description**
- **Members@odata.count**
- **Members**
- **Name**
- **Oem**

POST

Request:

```
POST https://{{ip}}/redfish/v1/AccountService/Roles
Content-Type: application/json
```

Example POST Request Body:

```
{
  "AssignedPrivileges": [
    "ConfigureUsers",
    "ConfigureManager",
    "ConfigureSelf",
    "Login",
    "ConfigureComponents"
  ],
  "Description":
  "TestRole User Role",
  "Id": "TestRole",
  "RoleId": "TestRole",
  "Enabled": true,
  "IsPredefined": true,
  "Name": "TestRole Role",
  "OemPrivileges":
  ["OemPowerControl",
  "OemClearLog"
  ]
}
```

8-4-1 Role

[GET] /redfish/v1/AccountService/Roles/{instance}

[PATCH] /redfish/v1/AccountService/Roles/{instance}

[DELETE] /redfish/v1/AccountService/Roles/{instance}

- **AssignedPrivileges**
- **Description**
- **Id**

- *IsPredefined*
- *Name*
- *RoleId*
- *OemPrivileges*
- *Actions*
- *Oem*

9. CertificateService

[GET] /redfish/v1/CertificateService

[POST] /redfish/v1/CertificateService/Actions/CertificateService.GenerateCSR

[POST] /redfish/v1/CertificateService/Actions/ CertificateService.ReplaceCertificate

- **Action**
- **Id**
- **Name**
- **Description**
- **CertificateLocations**
- **Oem**

POST

Request:

```
POST https://{{ip}}/redfish/v1/CertificateService/Actions/CertificateService.GenerateCSR
Content-Type: application/json
```

Example POST Request Body:

```
{
  "Country": "US",
  "State": "Oregon",
  "City": "Portland",
  "Organization": "Contoso",
  "OrganizationalUnit": "Service Processors",
  "CommonName": "manager.contoso.org",
  "AlternativeNames": [ "manager.contoso.com", "manager.contoso.us", "169.254.0.17" ],
  "Email": "admin@contoso.org",
  "KeyBitLength": 2048,
  "KeyUsage": [ "DigitalSignature" ],
  "ChallengePassword": "challengepassword",
  "GivenName": "userGivenName",
  "ContactPerson": "AMI Manager",
  "Initials": "userInitials",
  "Surname": "userSurname",
  "UnstructuredName": "userUnstructuredName",
  "CertificateCollection": {"@odata.id": "/redfish/v1/Managers/Self/NetworkProtocol/HTTPS/Certificates"}
}
```

Request:

```
POST https://{{ip}}/redfish/v1/CertificateService/Actions/CertificateService.ReplaceCertificate
Content-Type: application/json
```

Note: If use Certificate chain, CertificateType must be "PEMchain"

Example POST Request Body:

```
{
  "CertificateString": "-----BEGIN CERTIFICATE-----
\nMIEOzCCcAY0GawIBAgIAJ08c/Hd0c/0GMA0GCsQgSIB3DQEBcWUAMIG7MqSvCQYD\nvUQQG6EwJVU
zEQMA4GA1UECAwHR2VvcmdpYTERMA8GA1UEBwwlTm9yY3Jvc3BxNDYy\nnBgNVBAoAMK0FtZXJpY2FuIE1lZDZ0cmVudHMgSjW5O2JXUjYXRpb25hbCBMTEMgKFEFN\nnSSkxGzAZBgNVBAsMEINlcnZpY2UgUHJhYyY2VzZ29yc2EUMBIGA1UEAw\nwLWVnYXhYXjY5b20xHjAcBgkqhkiG9w0BCQEWD3NlCHBvcnRAYW1pLmNm\nvbTAEFw0xOTA4Mjc4bnZAZzA4MjMBAUMIG7MqSvCQYDVOQQG6EwJVUzEQMA4GA1UECAwHR2VvcmdpYTERMA8GA1UEBwwlTm9yY3Jvc3BxNDYy\nnBgNVBAoAMK0FtZXJpY2FuIE1lZDZ0cmVudHMgSjW5O2JXUjYXRpb25hbCBMTEMgKFEFNnSSkxGzAZBgNVBAsMEINlcnZpY2UgUHJhYyY2VzZ29yc2EUMBIGA1UEAw\nwLWVnYXhYXjY5b20xHjAcBgkqhkiG9w0BcQEWD3NlCHBvcnRAYW1pLmNmVnTC\nCASiWdQYJKoZIhvcNAQEBBQADggEPADCCAQoCuggEBAPlhY7RBUskLGB3yHZfiek9Zm9vJhe/1mRZlW\nTT778g8ySeo2L9Bliscptm\nTm\n2clMGBRwFgCjOyZqkldU2mu2zeALS31Bkxv12/OoLoG/MkvXc09MrNwWuE0\nQ2AZwgU7X+beKSAQAyZfZiW5Yf4hmadEtzh53rkd9mKYp101YfnAqZ+Zg9MxXuzl8TM\nnEgh7iemTtwozL7Hlwih6cIKNm/7m\nsl7LlIEQUP4wBTJBF1nmVe80fdNoDC+FB\nnvXwSuvH5wlH4Nd2hth16L6GRJrKGF\nE7FsqxVzBvB2anp8U44VVD69guPo47XlS\nn2yYXHPNwZmw9zm7md5TCRJLKT20CAwEA\nAaNAMd4wCQYDVR0TBAlwADALBgNVHQ8EBAMC\nBeAwJAyDVR0RBBoW64ILBwVnYXhY\nY5jb22CDE2OS4yNTQuMC4xZnANB\nGkq/nhkiG9w0BAQsFAAOCAQEAZ3ILV\nGGyVR6LJ+Au7gY5w9T+k+CpXgzorF\n+yRcSJo/hn/kfSMPpGH6yY+5j4Z9kQ57nTfnaBqm\nHnEhwhAQRtPVAPd3iKEYHNHO4u0g\nB4ZnkaI\nnyeLA4vM3KG5510Iry8oBhYuvv\nZwE3YhtYNNocZd1c5A8ZmpenS4ff\nPwWFGZGmV\nnfdDSGa4NdzLr1auPt5FUGbsm5\nV0FNPNhY\nNRPY5HQRMfYh+orv7275Jnxocr4B3\nncaq\nnUGNdPvVow5Qrmmn0W5Sjv285F3\nBieE1b6iSDkz14YlCr8twBeTq5g9c\n1qVh\nnY7Ms4UrZTjYhXq0oVgplADOn+LL9\nqEZ9MXAR6SkeQ\nn-----END CERTIFICATE\n-----
\n-----BEGIN RSA PRIVATE KEY-----
\nMIIEowIBAAKCAQEA+OfjTEFTmQsYHf\nidl+IST1mb28mf7/WZfMvZNPvDyLl6\njY\nuv0Glix21O6ZyUwYFHA\nWAKM7JmqSV1Yy7bN4AtLfUGS/HXb\n846Wbg8yS9XFzT0y\nus1bARTRDYDOMa7tf5sQpIBABjM\nVkhZJh/gdp0S3OHneur2T2YpinXTVH\n+cPn70UnD0zFe70XxMwQaHuJ6Z03\nCjOwrtMeXAlfipwgo2bt0awvsguJ8\nRBQJAFMkf/WeZv7\nnR902gML4UG9fBK68c\njnAi3gl3aG2EjouxXoZEmsoYU\nT5WyrFXMFVvZgenxTj\nhUNX\nnr2C4+jteVl\nbJlcc83BmbD30buYp\nlMJkEspBQIDAQABAoIB\nACTpiNgbOELmlk\nW\nup7z3ErA1jOe1/a\nW\nnW4ocx\nkNkY54m6jSrU\nlWPMfhmftN3dw1SEqz689Y\nDjrYC2\nnXNEZ877e7f\nnInc1\nI\nw\njyob7JlEay5N9G\nbcJxEMdtUB3ZM\nQ1nuT\nvGw8+B3e0HG\nnrDH8210M\nnAAAMUzQxZrTE6g\nteYkSfS\nyXgMc+X4i1\nhZuzA1IKa2uXk+6X\nnEtuCu\nnoadu5KmH\nM0Oxh5ph4Jc\nb1HgSxrV\njunsd+x12\nNPFcJchz4V5\nSCRQ6gDPI\nEZmrF1\nnTdnsW8fZ\nh6v6faHe1\nbCDrXIG3\nDw3DlQ\nwP\nHm7V\nk0TqToMgE\nEuc+DcL\ncmEun2iK\nnrWD13SEc\ngYEA\n/xyzJ0enwIE\nVuxHfz8H7ZwgY5\nk1j0ygzR\nFEGF+vrD\ni8a09HR+n\nb5KmqG1oZ\ni0Doratl\nwQb3Lj5ggoYR\nYYP1SPGq\nDFdaDgd\nn9jcu0V\nQpQ+5jsLB\nV03noA\nUmSEB9Yk3eGZ1XAZro+FzG\nb5BsZyaG0Q\nllnC\nCqGcJZ+G75\nlgi8CgYEA\n+b8j\nnKuoXrB\naBrGCs9880\nSpuebEQo7zZH9T\nvN+ea2ZR9N7c\nDOXsSpsTQs\nJ5Q4pwlhOD\nng0Jv3CFK\nCaK2mXA3S\nJ+UzlmvIPDg31\nY3qbpA+Z\nBYJG8r7\nv4uSj\nbBBFkxbX\nv\nU\nn1S8oV\nQbfljfdT\nfmpK5+TPT\nNig4C5IB2\nAuuJmZCgY\nBO+vYH\ni05FXD\nXqY\nnV\nOpr\nnuaTAAJA38dC803\n640RpkbXvd13\nNCQX\nVQUYtE0Y\nXkEIK83k\nf8kXkFph9P\nVCTniF31S7\nCevuxG\nWQdsKa7\nSol0yun3F4kD5\nJhTFI7pXK7ya8\nSTRdaA2v1z\nZ+IzazR4V\n\n5y82IGrYnd4gNcU\nZOVW/QKBgQCKdeub\nauMK51dxKA/9O3\nAi80/9+i8cr3B48\n2bE\nnycTSCD772p0R\nCymCMVjX40T\nOgqHEN3TCgU\nFtavlBZKwspY\nTz1W\nCqobOx+Q98\nnEa/9KD904e8\nJA5B6j\nvAM+cC8B\nWyg/ktb/2e\nViploGKvmlVz9/57\nmbduTLWElr\nn\nPn6qfQKBgEg\nL9ShURu6pytG\nlIF6CVPT1DhX\nXvzAvj8K\nWwdW\npwo3BF182T9\njNg\nnV\n441nirH4izd7Iz\nPNv56vb3F4D2\nlY4zAfW\nhfrMytrv8aKghD\nryZq5Q6mX\nmz5hq\nnd071CuwagoRn6UG5GZ\nWs+B/OH16xPYKwZmZOYEZaoE7ubEtzB7qW\nn-----END RSA PRIVATE KEY-----",
  "CertificateType": "PEM",
  "CertificateUri": "({@odata.id})/redfish/v1/Managers/Self/NetworkProtocol/HTTPS/Certificates/1"
}
```

9-1 CertificateLocations

[GET] /redfish/v1/CertificateService/CertificateLocations

- Id
- Name
- Description
- Links
 - Certificates
- Action
- Oem

10. Chassis Collection

[GET] /redfish/v1/Chassis

- **Description**
- **Name**
- **Members@odata.count**
- **Members**
- **Oem**

10-1 Chassis

[GET] /redfish/v1/Chassis/{instance}

[PATCH] /redfish/v1/Chassis/{instance}

[POST] /redfish/v1/Chassis/{instance}/Actions/Chassis.Reset

- **Id**
- **Name**
- **Description**
- **ChassisType**
- **Manufacturer**
- **Model**
- **SKU**
- **Sensors**
- **SerialNumber**
- **PartNumber**
- **PCleDevices**
- **AssetTag**
- **IndicatorLED**
- **Links**
 - **ComputerSystems**
 - **ComputerSystems@odata.count**
 - **ManagedBy**
 - **ManagedBy@odata.count**
 - **Drives**
 - **Drives @odata.count**
 - **Storage**
 - **Storage@odata.count**
 - **ResourceBlocks**
 - **ResourceBlocks @odata.count**
 - **ContainedBy**
 - **Contains**
 - **Contains @odata.count**
 - **PowerBy**
 - **PowerBy @odata.count**
 - **CooledBy**
 - **CooledBy @odata.count**
 - **ManagersInChassis**
 - **ManagersInChassis @odata.count**

- Processors
- Processors @odata.count
- Actions
- Status
- LogServices
- Thermal
- Power
- PowerState
- NetworkAdapters
- Assembly
- Oem
- UUID
- Location
- HeightMm
- WidthMm
- DepthMm
- WeightKg
- MediaControllers
- EnvironmentalClass

POST

Request:

```
POST https://{{ip}}/redfish/v1/Chassis/Self/Actions/Chassis.Reset
Content-Type: application/json
```

Request Body:

The *ResetType* can be one of the following values: "On", "ForceOff", "GracefulShutdown", "ForceRestart".

Example POST Request Body:

```
{
  "ResetType": "On"
}
```

10-1-1 Power

[GET] /redfish/v1/Chassis/{instance} /Power

[PATCH] /redfish/v1/Chassis/{instance}/Power

- Description
- Id
- Name
- PowerControl
 - Name
 - MemberId
 - PowerMetrics
 - IntervallnMin
 - MinConsumedWatts

- *MaxConsumedWatts*
- *AverageConsumedWatts*
- *RelatedItem@odata.count*
- *PhysicalContext*
- *PowerConsumedWatts*
- *PowerRequestedWatts*
- *PowerAvailableWatts*
- *PowerCapacityWatts*
- *PowerAllocatedWatts*
- *PowerLimit*
- *LimitInWatts*
- *LimitException*
- *CorrectionInMs*
- *PowerControl@odata.count*
- *Voltage*
 - *MemberId*
 - *Name*
 - *SensorNumber*
 - *Status*
 - *ReadingVolts*
 - *UpperThresholdNonCritical*
 - *UpperThresholdCritical*
 - *LowerThresholdNonCritical*
 - *LowerThresholdCritical*
 - *MinReadingRange*
 - *MaxReadingRange*
 - *RelatedItem*
 - *OwnerLUN*
 - *UpperThresholdFatal*
 - *LowerThresholdFatal*
 - *PhysicalContext*
 - *RelatedItem (RelatedItem@odata.count)*
- *Voltages@odata.count*
- *PowerSupply*
 - *MemberId*
 - *Name*
 - *LineInputVoltage*
 - *PowerCapacityWatts*
 - *LastPowerOutputWatts*
 - *Model*
 - *FirmwareVersion*
 - *SerialNumber*
 - *PowerInputWatt*
 - *PowerOutputWatts*
 - *PowerSupplyType*

- *LineInputVoltageType*
- *PartNumber*
- *SparePartNumber*
- *Status*
- *Location*
- *EfficiencyPercent*
- *HotPluggable*
- *RelatedItem*
- *Redundancy*
- *Oem*

10-1-2 LogServices (Support services after version 12.41.07)

[GET] /redfish/v1/Chassis/{instance}/LogServices

- *Description*
- *Members*
- *Members@odata.count*
- *Name*
- *Oem*

10-1-2-1 Log Service

[GET] /redfish/v1/Chassis/{instance}/LogServices/Logs

[PATCH] /redfish/v1/Chassis/{instance}/LogServices/Logs

[POST] /redfish/v1/Chassis/{instance}/LogServices/Log/Actions/LogServices.ClearLog

- *Id*
- *Name*
- *Description*
- *ServiceEnabled*
- *MaxNumberOfRecords*
- *OverWritePolicy*
- *DateTime*
- *DateTimeLocalOffset*
- *Actions*
- *Status*
- *Entries*
- *LogEntry Type*
- *Oem*

POST

Request:

```
POST https://{{ip}}/redfish/v1/Chassis/Self/LogServices/SEL/Actions/LogServices.ClearLog
Content-Type: application/json
```

Request Body:

```
{  
}
```

10-1-2-1-1 Entry Collection

[GET] /redfish/v1/Chassis/{instance}/LogServices/Log/Entries

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

10-1-2-1-1-1 Entry

[GET] /redfish/v1/Chassis/{instance}/LogServices/Log/Entries/{instance}

- **Id**
- **Name**
- **Description**
- **Severity**
- **Created**
- **EventTimestamp**
- **EntryType**
- **EntryCode**
- **SensorType**
- **SensorNumber**
- **Message**
- **MessageId**
- **Links**
 - **OriginOfConfition**
- **Oem**
- **EventId**
- **MessageArgs**
- **OemLogEntryCode**
- **OemSensorType**

10-1-3 Sensor Collection

[GET] /redfish/v1/Chassis/{instance}/Sensors

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

10-1-3-1 Sensor

[GET] /redfish/v1/Chassis/{instance}/Sensors/{instance}

- **PeakReading**
- **PeakReadingTime**
- **Reading**
- **ReadingType**
- **Oem**
- **Accuracy**
- **AdjustedMaxAllowableOperatingValue**
- **AdjustedMinAllowableOperatingValue**
- **ApparentVA**
- **ElectricalContext**
- **LoadPercent**
- **Location**
- **MaxAllowableOperatingValue**
- **MinAllowableOperatingValue**
- **PhysicalContext**
- **PhysicalSubContext**
- **PowerFactor**
- **Precision**
- **ReactiveVAR**
- **ReadingRangeMax**
- **ReadingRangeMin**
- **ReadingUnits**
- **SensingFrequency**
- **SensorResetTime**
- **Status**
- **Thresholds**
- **VoltageType**

10-1-3-2 Sensor Energy

[GET] /redfish/v1/Chassis/{instance}/Sensors/Energy

- **Id**
- **Name**
- **Oem**
- **Reading**
- **ReadingType**
- **PeakReading**
- **PeakReadingTime**

10-1-3-3 Sensor Power

[GET] /redfish/v1/Chassis/{instance}/Sensors/Power

- *Id*
- *Name*
- *PeakReading*
- *PeakReadingTime*
- *Reading*
- *ReadingType*

10-1-4 Thermal

[GET] /redfish/v1/Chassis/{instance} /Thermal

- *Description*
- *Id*
- *Name*
- *Temperatures*
 - *Name*
 - *MemberId*
 - *SensorNumber*
 - *Status*
 - *ReadingCelsius*
 - *UpperThresholdNonCritical*
 - *UpperThresholdCritical*
 - *LowerThresholdNonCritical*
 - *LowerThresholdCritical*
 - *PhysicalContext*
 - *OwnerLUN*
 - *UpperThresholdFatal*
 - *LowerThresholdFatal*
 - *MinReadingRangeTemp*
 - *MaxReadingRangeTemp*
 - *RelatedItem*
 - *DeltaReadingCelsius*
 - *DeltaPhysicalContext*
 - *MaxAllowableOperatingValue*
 - *MinAllowableOperatingValue*
 - *AdjustedMaxAllowableOperatingValue*
 - *AdjustedMinAllowableOperatingValue*
- *Fan*
 - *MemberId*
 - *Name*
 - *PhysicalContext*
 - *Status*
 - *Reading*
 - *LowerThresholdNonCritical*
 - *LowerThresholdCritical*
 - *MinReadingRange*

- *MaxReadingRange*
- *RelatedItem (RelatedItem@odata.count)*
- *OwnerLUN*
- *UpperThresholdNonCritical*
- *UpperThresholdCritical*
- *UpperThresholdFatal*
- *LowerThresholdFatal*
- *Redundancy*
- *HotPluggable*
- *Location*
- *SensorNumebr*
- *Oem*
- *Redundancy*
- *Actions*

10-1-4-1 FanprofileService (GBT)

[GET] /redfish/v1/Chassis/{instance}/Thermal/FanprofileService

- *Fanprofile*
- *Id*
- *Name*
- *SupportPCIEDevice*

10-1-4-1-1 Fanprofile

[GET] /redfish/v1/Chassis/{instance}/Thermal/FanprofileService/Fanprofile

[PUT] /redfish/v1/Chassis/{instance}/Thermal/FanprofileService/Fanprofile

- *Id*
- *Name*
- *arrProfile*
 - *arrPolicy*
 - *arrDuty*
 - *arrFanSensor*
 - *arrHexDeviceID*
 - *arrHexVendorID*
 - *arrRef*
 - *arrSensor*
 - *iAmbientSensor*
 - *iAmbientSensorTemp*
 - *iCpuTdp*
 - *ilnSDR*
 - *ilnitDuty*
 - *iPCIEDeviceEnable*
 - *iPolicyType*
 - *iSensorCodee*
 - *strName*
 - *strVersion*
- *strMode*

- *strVersion*

10-1-4-1-2 SupportPCIEDevice

[GET] /redfish/v1/Chassis/{instance}/Thermal/FanprofileService/SupportPCIEDevice

[PUT] /redfish/v1/Chassis/{instance}/Thermal/FanprofileService/SupportPCIEDevice

- *Id*

- *Name*

- *arrPCIEDevices*

- *hexDeviceID*

- *hexVendorID*

- *strName*

- *strVersion*

10-1-5 NetworkAdapterCollection

[GET] /redfish/v1/Chassis/{instance}/NetworkAdapters

- *Description*

- *Members*

- *Members@odata.count*

- *Name*

- *Oem*

10-1-5-1 NetworkAdapter

[GET] /redfish/v1/Chassis/{instance}/NetworkAdapters/{instance}

- *Members*

- *Members@odata.count*

- *Name*

- *Description*

- *Oem*

10-1-6 PCIeDevice Collection

[GET] /redfish/v1/Chassis/{instance}/PCIeDevices/{instance}

- *Description*

- *Members*

- *Members@odata.count*

- *Name*

- *Description*

- *Oem*

10-1-6-1 PCIeDecice

[GET] /redfish/v1/Chassis/{instance}/PCIeDevices/{instance}

- *Id*

- *Name*

- *Description*

- *Status*

- *Manufacturer*

- *Model*
- *SKU*
- *SerialNumber*
- *PartNumber*
- *AssetTag*
- *FirmwareVersion*
- *Links*
- *PCleFunctions*
- *PCleInterface*
- *Oem*
- *DeviceType*
- *Assembly*

10-1-6-1-1 PCIeFunction

[GET] /redfish/v1/Chassis/{instance}/PCleDevices/{instance}/PCleFunctions/{instance}

Id

- *Name*
- *Description*
- *Status*
- *DeviceClass*
- *VendorId*
- *ClassCode*
- *Link*
- *FunctionId*
- *FunctionType*
- *DeviceId*
- *RevisionId*
- *SubsystemId*
- *SubsystemVendorId*
- *Actions*

11. CompositionService

[Get] /redfish/v1/CompositionService

[Patch] /redfish/v1/CompositionService

- **Description**
- **Id**
- **Name**
- **ResourceBlocks**
- **ResourceZones**
- **ServiceEnabled**
- **Status**
- **Oem**

11-1 ResourceBlocks Collection

[Get] /redfish/v1/CompositionService/ResourceBlocks

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

11-1-1 ResourceBlocks

[Get] /redfish/v1/CompositionService/ResourceBlocks/{instance}

[Patch] /redfish/v1/CompositionService/ResourceBlocks/{instance}

- **Id**
- **Name**
- **Description**
- **Status**
- **CompositionStatus**
 - **Reserved**
 - **MaxCompositions**
 - **CompositionState**
- **ResourceBlockType**
- **Processors**
- **Memory**
- **Oem**
- **Link**
 - **Chassis**
- **Storage**
- **SimpleStorage**
- **Drivers**
- **EthernetInterfaces**

11-2 ResourceZones Collection

[Get] /redfish/v1/CompositionService/ResourceBlocks

- **Description**
- **Members**
- **Members@odata.count**
- **Name**

11-2-1 ResourceZones

[Get] /redfish/v1/CompositionService/ResourceBlocks/{instance}

- **Id**
- **Name**
- **Description**
- **Links**
 - **Oem**
 - **ResourceBlocks**
- **Status**

12. AMI OEM Entities - Configuration

[Get] /redfish/v1/Oem/Ami/Configuration

- **Id**
- **Name**
- **CertificateAuthorityUrl**
- **Oem**

13. EventService

[GET] /redfish/v1/EventService

[PATCH] /redfish/v1/EventService

[POST] /redfish/v1/EventService/Actions/EventService.SubmitTestEvent

- **Actions**
- **DeliveryRetryAttempts**
- **DeliveryRetryIntervalSeconds**
- **Description**
- **EventFormatTypes**
- **Id**
- **Name**
- **ServiceEnabled**
- **Status**
- **Subscriptions**
- **ServerSentEventUri**
- **SSEFilterPropertiesSupported**
- **Oem**
- **RegistryPrefixes**
- **ResourceTypes**
- **SubordinateResourcesSupported**
- **SMTP**
 - **Authentication**
 - **ConnectionProtocol**
 - **Password**
 - **Port**
- **ServiceEnabled**

POST

Request:

```
POST https://{{ip}}/redfish/v1/EventService/Actions/EventService.SubmitTestEvent
Content-Type: application/json
```

EventService.SubmitTestEvent can test using below RegistryPrefixes MessageId

- Base1.5.0
- EventLog.1.0.0
- HttpStatus.1.0.0
- IPMI.1.0.0
- Security.1.0.0
- SyncAgent.1.0.0

https://{{ip}}/redfish/v1/Registries/{{Registry_instance.json}}

Eg: https://{{ip}}/redfish/v1/Registries/Base.1.5.0.json

Example: Base.1.5.0 [PropertyValueNotInList as MessageId]

Example POST Request Body:

```
{
  "EventTimestamp":"2019-09-20T23:04:09+02:00",
  "EventId":"1531584914",
  "OriginOfCondition":"/redfish/v1/Chassis/Self",
  "MessageId":"PropertyValueNotInList",
  "MessageArgs":["Lit","IndicatorLED"],
  "Severity":"Warning"
}
```

13-1 Subscription Collection

[GET] /redfish/v1/EventService/Subscriptions

[POST] /redfish/v1/EventService/Subscriptions

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

POST

Request:

```
POST https://{{ip}}/redfish/v1/EventService/Subscriptions
Content-Type: application/json
```

Example POST Request Body:

```
{
  "Context": "Rocket All",
  "Destination": "http://10.1.112.223:7628/",
  "EventFormatType": "Event",
  "Protocol": "Redfish",
  "RegistryPrefixes":["SyncAgent.1.0.0","Base.1.5.0","EventLog.1.0.0"],
  "ResourceTypes":["Chassis","Systems","EventService"]
}
```

Empty or Absent RegistryPrefixes, ResourceTypes and Absent EventFormatType:

RegistryPrefixes, ResourceTypes values are absent or empty are accepted in POST call. In this case service shall sent events with any ResourceTypes or any RegistryPrefixes. If EventFormatType property was absent on POST call then default value will be Event.

Example POST Request Body:

```
{
  "Context": "Rocket All",
  "Destination": "http://10.1.112.223:7628/",
  "Protocol": "Redfish",
  "RegistryPrefixes": [],
  "ResourceTypes": []
}
```

13-1-1 Subscription

[GET] /redfish/v1/EventService/Subscriptions/{instance}
[PATCH] /redfish/v1/EventService/Subscriptions/{instance}
[DELETE] /redfish/v1/EventService/Subscriptions/{instance}

- **Id**
- **Name**
- **Description**
- **EventTypes**
- **Context**
- **SubscriptionType**
- **Protocol**
- **MessageIds**
- **OriginResources**
- **OriginResources@odata.count**
- **Status**
- **DeliveryRetryPolicy**
- **Oem**
- **Destination**
- **Actions**
- **SubordinateResources**
- **EventFormarType**
- **RegistryPrefixes**
- **ResourceTypes**
- **MetricReportDefinitions**
- **DeliveryRetryPolicy**

13-1-2 Subscription Test Event

[GET] /redfish/v1/EventService/Subscriptions/SubmitTestEventActionInfo

- **Description**
- **Id**
- **Name**
- **Parameters**
- **Oem**

14. JsonSchemas Collection

[Get] /redfish/v1/JsonSchemas

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

14-1 JsonSchemas

[Get] /redfish/v1/JsonSchemas/{instance}

- **Oem**
- **Id**
- **Name**
- **Description**
- **Languages**
- **Schema**
- **Location**
- **Actions**

15. Manager Collection

[GET] /redfish/v1/Managers

- **Description**
- **Members**
- **Members@odata.count**
- **Name**

15-1 Manager

[GET] /redfish/v1/Managers/{instance}

[PATCH] /redfish/v1/Managers/{instance}

[POST] /redfish/v1/Managers/{instance}/Actions/Manager.Reset

[POST] /redfish/v1/Managers/{instance}/Actions/Oem/AMIManager.RedfishDBReset

- **Id**
- **Name**
- **Description**
- **ManagerType**
- **Links**
 - **ManagerForServers**
 - **ManagerForServers@odata.count**
 - **ManagerForChassis**
 - **ManagerForServers@odata.count**
- **ManagerInChassis- ServiceEntryPointUUID**
- **UUID**
- **Model**
- **DateTime**
- **DateTimeLocalOffset**
- **FirmwareVersion**
- **SerialConsole**
- **CommandShell**
- **GraphicalConsole**
- **Actions**
- **Status**
- **EthernetInterfaces**
- **SerialInterfaces**
- **NetworkProtocol**
- **LogServices**
- **HostInterfaces**
- **PowerState**
- **Redundancy@odata.count**
- **Oem**
 - **VirtualMedia**
 - **ManagerServiceInfo**
 - **CommandShellServiceInfo**
 - **Links**

- **NetworkProtocol**
- **VirtualMedia**
- **AutoDSTEnabled**

POST

Request:

```
POST https://{{ip}}/redfish/v1/Managers/Self/Actions/Manager.Reset
Content-Type: application/json
```

Request Body:

The ResetType can be one of the following values: "On", "ForceOff", "GracefulShutdown", "ForceRestart".

Example POST Request Body:

```
{
  "ResetType": "On"
}
{
  "ResetType": "On"
}
```

Request:

```
POST https://{{ip}}/redfish/v1/Managers/Self/Actions/RedfishDBReset
Content-Type: application/json
```

Example POST Request Body:

```
{
  "RedfishDBResetType": "ResetAll"
}
```

15-1-1 EthernetInterfaces Collection

[Get] /redfish/v1/Managers/{instance}/EthernetInterfaces

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

15-1-1-1 EthernetInterfaces

[Get] /redfish/v1/Managers/{instance}/EthernetInterfaces/bond0

[PATCH] /redfish/v1/Managers/{instance}/EthernetInterfaces/{{manager_ethifc_instance}}

- **Id**
- **Name**
- **Description**
- **Status**
- **InterfaceEnabled**
- **PermanentMACAddress**
- **MACAddress**
- **SpeedMbps**
- **AutoNeg**
- **FullDuplex**
- **MTUSize**
- **HostName**
- **FQDN**
- **MaxIPv6StaticAddresses**
- **VLAN**
- **Ipv4Addresses**
- **Ipv6Addresses**
- **IPv6DefaultGateway**
- **NameServers**
- **LinkStatus**
- **DHCPv4**
- **Oem**
- **UefiDevicePath**
- **StatelessAddressAutoConfig**
- **Ipv6StaticAddresses**
- **VLANs**
- **Actions**
- **DHCPv6**
- **IPv6StaticDefaultGateways**
- **IPv4StaticAddresses**

[GET] /redfish/v1/Managers/Self/EthernetInterfaces/eth0

- **Id**
- **Name**
- **Description**
- **InterfaceEnabled**
- **PermanentMACAddress**
- **MACAddress**
- **LinkStatus**
- **Oem**
- **UefiDevicePath**
- **Status**
- **SpeedMbps**
- **StatelessAddressAutoConfig**
- **AutoNeg**
- **FullDuplex**
- **MTUSize**
- **HostName**
- **FQDN**
- **MaxIPv6StaticAddresses**
- **VLAN**
- **Ipv4Addresses**
- **Ipv6Addresses**
- **Ipv6DefaultGateway**
- **NameServers**
- **StaticNameServers**
- **VLANs**
- **Actions**
- **DHCPv4**
- **DHCPv6**
- **IPv6StaticDefaultGateways**
- **IPv4StaticAddresses**
- **IPv6AddressPolicyTable**

[GET] /redfish/v1/Managers/Self/EthernetInterfaces/eth1

- **Id**
- **Name**
- **Description**
- **InterfaceEnabled**
- **PermanentMACAddress**
- **MACAddress**
- **LinkStatus**
- **Oem**
- **UefiDevicePath**
- **Status**
- **SpeedMbps**
- **StatelessAddressAutoConfig**

- *AutoNeg*
- *FullDuplex*
- *MTUSize*
- *HostName*
- *FQDN*
- *MaxIPv6StaticAddresses*
- *VLAN*
- *Ipv4Addresses*
- *Ipv6Addresses*
- *Ipv6StaticAddresses*
- *Ipv6DefaultGateway*
- *NameServers*
- *VLANs*
- *Actions*
- *DHCPv4*
- *DHCPv6*
- *IPv6StaticDefaultGateways*
- *IPv4StaticAddresses*

[GET] /redfish/v1/Managers/Self/EthernetInterfaces/usb0

- *Id*
- *Name*
- *Description*
- *Status*
- *InterfaceEnabled*
- *PermanentMACAddress*
- *MACAddress*
- *Ipv4Addresses*
- *Ipv6Addresses*
- *LinkStatus*
- *Oem*
- *UefiDevicePath*
- *SpeedMbps*
- *StatelessAddressAutoConfig*
- *AutoNeg*
- *FullDuplex*
- *MTUSize*
- *HostName*
- *FQDN*
- *MaxIPv6StaticAddresses*
- *VLAN*
- *Ipv6StaticAddresses*
- *Ipv6DefaultGateway*
- *NameServers*
- *VLANs*
- *Actions*

- DHCPv4
- DHCPv6
- IPv6StaticDefaultGateways
- IPv4StaticAddresses

15-1-2 CertificateCollection

[Get] /redfish/v1/Managers/{instance}/NetworkProtocol/HTTPS/Certificates

- Description
- Members
- Members@odata.count
- Name
- Oem

15-1-3 Factory Reset ActionInfo

[GET] /redfish/v1/Managers/{instance}/RedfishDBResetActionInfo

- Description
- Id
- Name
- Parameters

15-1-4 HostInterfaces Collection

[Get] /redfish/v1/Managers/{instance}/HostInterfaces

- Description
- Members
- Members@odata.count
- Name
- Oem

15-1-4-1 HostInterfaces

[Get] /redfish/v1/Managers/{instance}/HostInterfaces/{instance}

[PATCH] /redfish/v1/Managers/{instance}/HostInterfaces/{instance}

- Id
- Name
- Description
- HostInterfaceType
- Status
- InterfaceEnabled
- ExternallyAccessible
- AuthenticationModes
- KernelAuthRoleId
- KernelAuthEnabled
- FirmwareAuthRoleId
- FirmwareAuthEnabled
- Links
- ComputerSystems@odata.count

- **ComputerSystems**
- **CredentialBootstrappingRole**
- **KernelAuthRole**
- **FirmwareAuthRole**
- **HostEthernetInterfaces**
- **ManagerEthernetInterface**
- **NetworkProtocol**
- **Oem**
- **AuthNoneRoleId**
- **CredentialBootstrapping**
 - **Enabled**
 - **EnableAfterReset**
 - **RoleId**

15-1-4-2 HostEthernetInterface Collection

[GET] /redfish/v1/Managers/Self/HostInterfaces/Self/HostEthernetInterfaces

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

15-1-5 LogServices Collection

[GET] /redfish/v1/Managers/{instance}/LogServices

[POST] /redfish/v1/Managers/{instance}/LogServices/AuditLog/Actions/LogService.ClearLog

[POST] /redfish/v1/Managers/{instance}/LogServices/EventLog/Actions/LogService.ClearLog

[POST] /redfish/v1/Managers/{instance}/LogServices/SEL/Actions/LogService.ClearLog

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

POST

Request:

```
POST https://{ip}/redfish/v1/Managers/Self/LogServices/AuditLog/Actions/LogService.ClearLog
https://{ip}/redfish/v1/Managers/Self/LogServices/EventLog/Actions/LogService.ClearLog
https://{ip}/redfish/v1/Managers/Self/LogServices/SEL/Actions/LogService.ClearLog
Content-Type: application/json
```

Example POST Request Body:

```
{
}
```

15-1-5-1 LogServices

[GET] /redfish/v1/Managers/{instance}/LogServices/{instance}

[PATCH] /redfish/v1/Managers/{instance}/LogServices/{instance}

- **Id**
- **Name**
- **Description**
- **ServiceEnabled**
- **MaxNumberOfRecords**
- **OverWritePolicy**
- **DateTime**
- **DateTimeLocalOffset**
- **Actions**
- **Status**
- **Entries**
- **LogEntry Type**
- **Oem**

15-1-5-1-1 Log Entry Collection

[GET] /redfish/v1/Managers/{instance}/LogServices/{instance}/Entries

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

15-1-5-1-1-1 Log Entry

[GET] /redfish/v1/Managers/Self/LogServices/AuditLog/Entries/{instance}

- **Id**
- **Name**
- **Description**
- **Severity**
- **Created**
- **EventTimestamp**
- **EntryType**
- **Message**
- **MessageId**
- **MessageArgs**
- **Oem**
- **EventId**
- **EntryCode**
- **SensorType**
- **SensorNumber**
- **Links**
 - **OriginOfCondition**
- **OemLogEntryCode**
- **OemSensorType**

[GET] /redfish/v1/Managers/Self/LogServices/EventLog/Entries/{instance}

- **Id**
- **Name**
- **Description**
- **Severity**
- **Created**
- **EventTimestamp**
- **EntryType**
- **EntryCode**
- **Message**
- **MessageId**
- **MessageArgs**
- **Links**
 - **OriginOfCondition**
- **Oem**
- **EventId**
- **SensorType**
- **OemLogEntryCode**
- **OemSensorType**

[GET] /redfish/v1/Managers/Self/LogServices/SEL/Entries/{instance}

- **Id**
- **Name**
- **Description**
- **Severity**
- **Created**
- **EventTimestamp**
- **EntryType**
- **EntryCode**
- **SensorType**
- **SensorNumber**
- **MessageId**
- **Oem**
- **EventId**
- **Message**
- **MessageArgs**
- **Links**
 - **OriginOfCondition**
- **OemLogEntryCode**
- **OemSensorType**

15-1-6 NetworkProtocol

[GET] /redfish/v1/Managers/{instance}/NetworkProtocol

[PATCH] /redfish/v1/Managers/{instance}/NetworkProtocol

- **Id**
- **Name**
- **Description**
- **HostName**
- **FQDN**
- **HTTPS**
- **SNMP**
 - **ProtocolEnabled**
 - **Port**
 - **AuthenticationProtocol**
 - **EncryptionProtocol**
 - **EngineId**
 - **EnableSNMPv1**
 - **EnableSNMPv2c**
 - **EnableSNMPv3**
- **VirtualMedia**
- **SSDP**
- **IPMI**
- **SSH**
- **KVMIP**
- **Status**
- **Oem**
- **Telnet**
- **Actions**
- **NTP**
 - **ProtocolEnabled**
 - **Port**
 - **NTPServers**

15-1-7 Reset ActionInfo

[GET] /redfish/v1/Managers/{instance}/ResetActionInfo

- **Description**
- **Id**
- **Name**
- **Parameters**

15-1-8 SerialInterfaces Collection

[GET] /redfish/v1/Managers/{instance}/SerialInterfaces

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

15-1-8-1 SerialInterfaces

[GET] /redfish/v1/Managers/{instance}/SerialInterfaces/{instance}

[PATCH] /redfish/v1/Managers/{instance}/SerialInterfaces/{instance}

- **Id**
- **Name**
- **Description**
- **Interface Enabled**
- **BitRate**
- **Parity**
- **DataBits**
- **StopBits**
- **FlowControl**
- **Oem**
- **SignalType**
- **ConnectorType**
- **PinOut**
- **Actions**

15-1-9 VirtualMedia Collection

[GET] /redfish/v1/Managers/{instance}/VirtualMedia

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

15-1-9-1 VirtualMedia Collection

[GET] /redfish/v1/Managers/{instance}/VirtualMedia/{instance}

[POST] /redfish/v1/Managers/{instance}/VirtualMedia/{instance}/Actions/VirtualMedia.InsertMedia

[POST] /redfish/v1/Managers/{instance}/VirtualMedia/{instance}/Actions/VirtualMedia.EjectMedia

[POST] /redfish/v1/Managers/{instance}/Actions/Oem/AMIVirtualMedia.ConfigureCDInstance

[POST] /redfish/v1/Managers/{instance}/Actions/Oem/AMIVirtualMedia.EnableRMedia

- **Actions**
- **ConnectedVia**
- **Description**
- **Id**
- **Image**

- *ImageName*
- *Inserted*
- *Name*
- *WriteProtected*
- *Oem*
- *MediaType*
- *TransferProtocolType*
- *TransferMethod*
- *UserName*

POST

Request:

```
POST https://{{ip}}/redfish/v1/Managers/Self/VirtualMedia/CD1/Actions/VirtualMedia.InsertMedia
Content-Type: application/json
```

Example POST Request Body:

```
{
  "Image": "nfs://10.0.125.169/home/tamil/images/images/ubuntu-14.04.1-desktop-amd64.iso",
  "TransferProtocolType": "NFS"
}
```

Request:

```
POST https://{{ip}}/redfish/v1/Managers/Self/VirtualMedia/CD1/Actions/VirtualMedia.EjectMedia
Content-Type: application/json
```

Example POST Request Body:

```
{}
```

Request:

```
POST https://{{ip}}/redfish/v1/Managers/Self/Actions/Oem/AMIVirtualMedia.ConfigureCDInstance
Content-Type: application/json
```

Example POST Request Body:

```
{
  "CDInstance": 4
}
```

Request:

```
POST https://{{ip}}/redfish/v1/Managers/Self/Actions/Oem/AMIVirtualMedia.EnableRMedia
Content-Type: application/json
```

Example POST Request Body:

```
{  
  "RMediaState": "Enable"  
}
```

16. InventoryDataMessage Registry File Collection

[GET] /redfish/v1/Registries

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

16-1 Message Registries

[GET] /redfish/v1/Registries/{instance}

- **Description**
- **Id**
- **Languages**
- **Name**
- **Oem**
- **RegistryPrefix**
- **RegistryVersion**
- **OwningEntity**
- **Messages**

16-2 Message Registries File

[GET] /redfish/v1/Registries/{instance.json}

- **Description**
- **Id**
- **Languages**
- **Messages**
- **Name**
- **OwningEntity**
- **RegistryPrefix**
- **RegistryVersion**
- **Oem**

17. Session Service

[GET] /redfish/v1/SessionService

[PATCH] /redfish/v1/SessionService

- **Description**
- **Id**
- **Name**
- **ServiceEnabled**
- **SessionTimeout**
- **Sessions**
- **Status**
- **Oem**
- **Actions**

17-1 Session Collection

[GET] /redfish/v1/SessionService/Sessions

[POST] /redfish/v1/SessionService/Sessions

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

POST

Request:

```
POST https://{{ip}}/redfish/v1/SessionService/Sessions
Content-Type: application/json
```

Example POST Request Body:

```
{
  "UserName": "admin",
  "Password": "password"
}
```

17-1-1 Session

[GET] /redfish/v1/SessionService/Sessions/{instance}

[DELETE] /redfish/v1/SessionService/Sessions/{instance}

- **Id**
- **Name**
- **Description**
- **UserName**
- **Oem**
- **Password**
- **Actions**

18. System Collection

[GET] /redfish/v1/Systems

[POST] /redfish/v1/Systems

@Redfish.CollectionCapabilities

- **Capabilities**
- **Members**
- **Members@odata.count**
- **Name**
- **Description**
- **Oem**

POST

Request:

```
POST https://{{ip}}/redfish/v1/Systems
Content-Type: application/json
```

Example POST Request Body:

```
{
  "Name": "NewSystem",
  "Links": {
    "ResourceBlocks": [{
      "@odata.id": "/redfish/v1/CompositionService/ResourceBlocks/ComputeBlock"
    }]
  },
  "HostName": "gigabyte"
}
```

18-1 Capabilities

[GET] /redfish/v1/Systems/Capabilities

- **Id**
- **Name**
- **Description**
- **Links**
 - **ResourceBlocks**
- **Boot**
- **HostName**

18-2 System

[GET] /redfish/v1/Systems/{instance}

[PATCH] /redfish/v1/Systems/{instance}

[POST] /redfish/v1/Systems/{instance}/Actions/ComputerSystem.Reset

- **Id**
- **Name**
- **Description**
- **SystemType**
 - **Physical**
- **Links**
 - **Oem**
 - **Chassis**
 - **Chassis@odata.count**
 - **ManagedBy**
 - **ManagedBy@odata.count**
- **AssetTag**
- **Manufacturer**
- **Model**
- **SKU**
- **SerialNumber**
- **PartNumber**
- **UUID**
- **IndicatorLED**
- **PowerState**
- **Boot**
- **BiosVersion**
- **ProcessorSummary**
 - **Count**
 - **Model**
 - **Status**
- **MemorySummary**
 - **TotalSystemMemoryGiB- Status**
 - **MemoryMirroring**
 - **TotalSystemPersistentMemoryGiB**
- **Actions**
- **Processors**
- **EthernetInterfaces**
- **SimpleStorage**
- **LogServices**
- **Status**
- **SecureBoot**
- **Bios**
- **Memory**
- **Storage**
- **NetworkInterfaces**

- **Oem**
- **SubModel**
- **Hostname**
- **TrustedModules**
- **HostingRoles**
- **HostedServices**
- **PCleDevices**
- **PCleDevices@odata.count**
- **PCleFunctions**
- **PCleFunctions@odata.count**
- **PowerRestorePolicy**

POST

Request:

```
POST https://{ip}/redfish/v1/Systems/Self/Actions/ComputerSystem.Reset
Content-Type: application/json
```

Request Body:

The ResetType can be one of the following values: "On", "ForceOff", "GracefulShutdown", "ForceRestart".

Example POST Request Body:

```
{
  "ResetType": "On"
}
```

18-2-1 BIOS

[GET] /redfish/v1/Systems/{instance}/Bios

[POST] /redfish/v1/Systems/{instance}/Bios/Actions/Bios.ResetBios

[POST] /redfish/v1/Systems/{instance}/Bios/Actions/Bios.ChangePassword

- **Oem**
- **Id**
- **Name**
- **Description**
- **AttributeRegistry**
- **Actions**
- **Attributes**

POST

Request:

```
POST https://{{ip}}/redfish/v1/Systems/Self/Bios/Actions/Bios.ResetBios
Content-Type: application/json
```

Example POST Request Body:

```
{
  "ResetType": "Reset"
}
```

Request:

```
POST https://{{ip}}/redfish/v1/Systems/Self/Bios/Actions/Bios.ChangePassword
Content-Type: application/json
```

Example POST Request Body:

```
{
  "PasswordName": "SETUP001",
  "OldPassword": "old",
  "NewPassword": "new"
}
```

19-2-1-1 BIOS SD

[POST] /redfish/v1/Systems/{instance}/Bios/SD

[PATCH] /redfish/v1/Systems/{instance}/Bios/SD

[PUT] /redfish/v1/Systems/{instance}/Bios/SD

- **Id**
- **Name**
- **Description**
- **AttributeRegistry**
- **Attributes**
- **Actions**

POST

Request:

```
POST https://{{ip}}/redfish/v1/Systems/Self/Bios/SD
Content-Type: application/json
```

Example POST Request Body:

```
{
  "Attributes": {
    "PCIS003": "Disabled"
  }
}
```

18-2-2 BootOption Collection

[GET] /redfish/v1/Systems/{instance}/BootOptions

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

18-2-2-1 BootOption Collection

[GET] /redfish/v1/Systems/{instance}/BootOptions/{instance}

- **Id**
- **Name**
- **Description**
- **BootOptionEnabled**
- **BootOptionReference**
- **DisplayName**
- **UefiDevicePath**
- **Alias**
- **Oem**
- **RelatedItem**
- **RelatedItem@odata.count**

18-2-3 EthernetInterfaces Collection

[GET] /redfish/v1/Systems/{instance}/EthernetInterfaces

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

18-2-3-1 EthernetInterfaces

[GET] /redfish/v1/Systems/{instance}/EthernetInterfaces/{instance}

- **Id**
- **Status**
- **MACAddress**
- **LinkStatus**
- **Links**
- **Name**

- *Oem*
- *UefiDevicePath*
- *InterfaceEnabled*
- *PermanentMACAddress*
- *Ipv4Addresses*
- *Ipv6Addresses*
- *Ipv6DefaultGateway*
- *VLANs*
- *Actions*
- *DHCPv4*
- *DHCPv6*

18-2-3-1-1 VLAN Network Interface Collection

[GET] /redfish/v1/Systems/{instance}/EthernetInterfaces/{instance}/VLANs

[POST] /redfish/v1/Systems/{instance}/EthernetInterfaces/{instance}/VLANs

- *Members*
- *Members@odata.count*
- *Name*
- *Description*
- *Oem*

POST

Request:

```
https://{ip}/redfish/v1/Systems/{system_instance}/EthernetInterfaces/{system_ethifc_instance}/VLANs
Content-Type: application/json
```

Example POST Request Body:

```
{
  "VLANId": 100,
  "VLANEnable": true,
  "VLANPriority": 2
}
```

18-2-3-1-1-1-1 VLANNetworkInterface

[GET] /redfish/v1/Systems/{instance}/EthernetInterfaces/{instance}/VLANs/{instance}

[PATCH] /redfish/v1/Systems/{instance}/EthernetInterfaces/{instance}/VLANs/{instance}

[DELETE] /redfish/v1/Systems/{instance}/EthernetInterfaces/{instance}/VLANs/{instance}

- **Id**
- **Name**
- **Description**
- **VLANEnable**
- **VLANId**
- **Oem**
- **Actions**

18-2-4 LogServices Collection

[GET] /redfish/v1/Systems/{instance}/LogServices

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

18-2-4-1 LogServices

[GET] /redfish/v1/Systems/{instance}/LogServices/{instance}

[PATCH] /redfish/v1/Systems/{instance}/LogServices/{instance}

[POST] /redfish/v1/Systems/{instance}/LogServices/{instance}/Actions/LogService.ClearLog

- **Oem**
- **Id**
- **Name**
- **Description**
- **ServiceEnabled**
- **MaxNumberOfRecords**
- **OverWritePolicy**
 - **WrapsWhenFull**
- **DateTime**
- **DateTimeLocalOffset**
- **Actions**
- **Status**
- **Entries**
- **LogEntry Type**

POST

Request:

```
POST https://{ip}/redfish/v1/Systems/Self/LogServices/BIOS/Actions/LogService.ClearLog
Content-Type: application/json
```

Example POST Request Body:

```
{
}
```

18-2-4-1-1 Log Entry Collection

[GET] /redfish/v1/Systems/{instance}/LogServices/{instance}/Entries

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

19-2-4-1-1-1 Log Entry

[GET] /redfish/v1/Systems/{instance}/LogServices/{instance}/Entries/{instance}

- **Id**
- **Name**
- **Description**
- **Severity**
- **Created**
- **EventId**
- **EventTimestamp**
- **EntryType**
- **EntryCode**
- **SensorType**
- **SensorNumber**
- **Message**
- **MessageId**
- **MessageArgs**
- **Oem**
- **Links**
 - **OriginOfCondition**
- **OemLogEntryCode**
- **OemSensorType**

18-2-5 Memory Collection

[GET] /redfish/v1/Systems/{instance}/Memory

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

18-2-5-1 Memory

[GET] /redfish/v1/Systems/{instance}/Memory/{instance}

- **Id**
- **Name**
- **Description**
- **MemoryType**
- **MemoryDeviceType**
- **CapacityMiB**

- *DataWidthBits*
- *BusWidthBits*
- *Manufacturer*
- *SerialNumber*
- *PartNumber*
- *AllowedSpeedsMHz*
- *DeviceLocator*
- *ErrorCorrection*
- *OperatingSpeedMhz*
- *Links*
 - *Chassis*
- *Status*
- *Oem*
- *BaseModuleType*
- *MemoryMedia*
- *Assembly*
- *FirmwareRevision*
- *FirmwareApiVersion*
- *FunctionClasses*
- *MaxTDPMilliWatts*
- *SecurityCapabilities*
- *SpareDeviceCount*
- *ConfigurationLocked*
- *RankCount*
- *MemoryLocation*
- *VolatileRegionSizeLimitMiB*
- *PersistentRegionSizeLimitMiB*
- *Regions*
- *OperatingMemoryModes*
- *PowerManagementPolicy*
- *IsSpareDeviceEnabled*
- *IsRankSpareEnabled*
- *VolatileRegionNumberLimit*
- *PersistentRegionNumberLimit*
- *VolatileRegionSizeMaxMiB*
- *PersistentRegionSizeMaxMiB*
- *AllocationIncrementMiB*
- *AllocationAlignmentMiB*
- *ModuleManufacturerID*
- *ModuleProductID*
- *MemorySubsystemControllerManufacturerID*
- *MemorySubsystemControllerProductID*
- *VolatileSizeMiB*
- *NonVolatileSizeMiB*
- *CacheSizeMiB*
- *LogicalSizeMiB*

- **Location**
- **Metrics**

18-2-6 MemoryDomains Collection

[GET] /redfish/v1/Systems/{instance}/MemoryDomains

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

18-2-7 NetworkInterface Collection

[GET] /redfish/v1/Systems/{instance}/NetworkInterfaces

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

18-2-7-1 NetworkInterface

[GET] /redfish/v1/Systems/{instance}/NetworkInterfaces/{instance}

- **Id**
- **Name**
- **Description**
- **Status**
- **Links**
- **NetworkDeviceFunctions**
- **Actions**

18-2-8 Processor Collection

[GET] /redfish/v1/Systems/{instance}/Processors

- **Members**
- **Members@odata.count**
- **Name**
- **Description**
- **Oem**

18-2-8-1 Processor

[GET] /redfish/v1/Systems/{instance}/Processors/{instance}

- **Id**
- **Name**
- **Description**
- **Socket**
- **Status**
- **State**

- **Health**
- **ProcessorType**
- **ProcessorArchitecture**
- **InstructionSet**
- **ProcessorId**
 - **IdentificationRegisters**
 - **EffectiveFamily**
 - **EffectiveModel**
- **Step**
- **Manufacturer**
- **Model**
- **MaxSpeedMHz**
- **TotalCores**
- **TotalThreads**
- **Links**
 - **Chassis**
- **Oem**
- **Actions**
- **SubProcessors**
- **Location**
- **Assembly**
- **MaxTDPWatts**
- **Metrics**
- **TDPWatts**
- **TotalEnabledCores**
- **UUID**
- **FPGA**
- **ProcessorMemory**
 - **CapacityMiB**
 - **IntegratedMemory**
 - **MemoryType**
 - **SpeedMHz**

18-2-9 SimpleStorage Collection

[GET] /redfish/v1/Systems/{instance}/SimpleStorage

- **Members**
- **Members@odata.count**
- **Name**
- **Description**
- **Oem**

18-2-9-1 SimpleStorage

[GET] /redfish/v1/Systems/{instance}/SimpleStorage/{instance}

- **Id**
- **Name**
- **Description**
- **Links**
- **Oem**
- **UefiDevicePath**
- **Status**
- **Actions**

18-2-10 Storage Collection

[Get] /redfish/v1/Systems/{instance}/Storage

- **Members**
- **Members@odata.count**
- **Name**
- **Description**
- **Oem**

18-2-10-1 Storage

[GET] /redfish/v1/Systems/{instance}/Storage/{instance}

- **Id**
- **Name**
- **Description**
- **Oem**
- **Status**
- **Links**
- **StorageControllers@odata.count**
- **StorageControllers**
- **Drives@odata.count**
- **Drives**
- **Volumes**
- **Redundancy@odata.count**

19. RedundancyTaskService

[GET] /redfish/v1/TaskService

- **CompletedTaskOverWritePolicy**
- **DateTime**
- **Description**
- **Id**
- **LifeCycleEventOnTaskStateChange**
- **Name**
- **ServiceEnabled**
- **Status**
- **Tasks**
- **Oem**
- **Actions**

19-1 Task Collection

[GET] /redfish/v1/TaskService/Tasks

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

19-1-1 Task

[GET] /redfish/v1/TaskService/Tasks/{instance}

[DELETE] /redfish/v1/TaskService/Tasks/{instance}

- **Oem**
- **Id**
- **Name**
- **Description**
- **TaskState**
- **StartTime**
- **EndTime**
- **TaskStatus**
- **Messages**
- **Actions**
- **HidePayload**
- **PercentComplete**
- **Payload**

20. TelemetryService

[Get] /redfish/v1/TelemetryService

[POST] /redfish/v1/TelemetryService/Actions/TelemetryService.SubmitTestMetricReport

[PATCH] /redfish/v1/TelemetryService

- **Oem**
- **Id**
- **MetricDefinitions**
- **MetricReportDefinitions**
- **MetricReports**
- **Triggers**
- **Status**
- **Name**
- **MaxReports**
- **MinCollectionInterval**
- **SupportedCollectionFunctions**
- **Actions**
- **LogService**
- **Description**
- **ServiceEnabled**
- **SupportedCollectionFunctions@Redfish.AllowableValues**

POST

Request:

```
POST https://{{ip}}/redfish/v1/TelemetryService/Actions/TelemetryService.SubmitTestMetricReport
Content-Type: application/json
```

Example POST Request Body:

```
{
  "MetricReportName": "Average2",
  "GeneratedMetricReportValues": [{
    "MetricId": "Temp_average_reading_Average",
    "MetricProperty": "/redfish/v1/Chassis/Self/Thermal#/Temperatures/0/ReadingCelsius",
    "MetricValue": "23",
    "Timestamp": "2019-07-01T06:05:52Z"
  }]
}
```

20-1 MetricReportLog Collection

[Get] /redfish/v1/TelemetryService/LogServices

[POST] /redfish/v1/TelemetryService/LogService/Actions/LogService.ClearLog

- **Description**
- **Members**

- *Members@odata.count*
- *Name*
- *Oem*

POST

Request:

```
POST https://{{ip}}/redfish/v1/TelemetryService/LogService/Actions/LogService.ClearLog
Content-Type: application/json
```

Example POST Request Body:

```
{
}
```

20-1-1 MetricReportLog

[Get] /redfish/v1/TelemetryService/LogServices

[Post] redfish/v1/TelemetryService/LogServices/Actions/LogService.ClearLog

- *Id*
- *Name*
- *Description*
- *ServiceEnabled*
- *MaxNumberOfRecords*
- *OverWritePolicy*
- *Actions*
- *Status*
- *Entries*
- *DateTime*
- *DateTimeLocalOffset*
- *Oem*
- *LogEntryType*

POST

Request:

```
POST https://{{ip}}/TelemetryService/LogServices/Actions/LogService.ClearLog
Content-Type: application/json
```

Example POST Request Body:

```
{
}
```

20-1-1-1-1 Entries Collection

[Get] /redfish/v1/TelemetryService/LogServices/Entries

- **Description**
- **Members**
- **Members@odata.count**
- **Name**
- **Oem**

20-1-1-1-1-1 Entries

[Get] /redfish/v1/TelemetryService/LogServices/Entries/{instance}

- **Id**
- **Name**
- **Description**
- **Severity**
- **Created**
- **EntryType**
- **EntryCode**
- **Message**
- **MessageId**
- **MessageArgs**
- **Links**
 - **OriginOfCondition**
- **Oem**
- **EventId**
- **EventTimestamp**
- **SensorType**
- **SensorNumber**
- **OemLogEntryCode**
- **OemSensorType**

20-2 MetricDefinitions Collection

[Get] /redfish/v1/TelemetryService/MetricDefinitions

- **Members**
- **Members@odata.count**
- **Name**

20-2-1 MetricDefinitions

[Get] /redfish/v1/TelemetryService/MetricDefinitions/{instance}

- **Id**
- **Name**
- **MetricType**
- **MetricDataType**
- **Implementation**
- **Units**
- **IsLinear**

- **MetricProperties**
- **Precision**
- **Accuracy**

20-3 MetricReportDefinition Collection

[Get] /redfish/v1/TelemetryService/MetricReportDefinitions

[POST] /redfish/v1/TelemetryService/MetricReportDefinitions

- **Members**
- **Members@odata.count**
- **Name**

POST

Request:

```
POST https://{{ip}}/redfish/v1/TelemetryService/MetricReportDefinitions
Content-Type: application/json
```

Example POST Request Body:

```
{
  "Id": "Voltage_Report",
  "Name": "Voltage_Report",
  "Schedule": {
    "RecurrenceInterval": "PT20S"
  },
  "MetricReportDefinitionType": "Periodic",
  "MetricReport": {
    "@odata.id": "/redfish/v1/TelemetryService/MetricReports/Voltage_Report",
    "MetricProperties": ["/redfish/v1/Chassis/Self/Power#/Voltages/0/ReadingVolts"]
  }
}
```

20-3-1 MetricReportDefinitions

[Get] /redfish/v1/TelemetryService/MetricReportDefinitions/{instance}

[Delete] /redfish/v1/TelemetryService/MetricReportDefinitions/{instance} [PATCH] /redfish/v1/TelemetryService/MetricReportDefinitions/{instance}

- **Id**
- **Name**
- **Schedule**
- **MetricReportDefinitionType**
- **Status**
- **MetricReport**
- **Metrics/MetricProperties**
- **MetricReportDefinitionEnable**
- **ReportTimespan**
- **ReportActions**

- **ReportUpdates**
- **Metrics**
 - **MetricProperties**

20-4 MetricReports Collection

[Get] /redfish/v1/TelemetryService/MetricReports

- **Members**
- **Members@odata.count**
- **Name**

20-4-1 MetricReports

[Get] /redfish/v1/TelemetryService/MetricReports/{instance}

- **Id**
- **Name**
- **MetricReportDefinition**
- **Timestamp**
- **ReportSequence**
- **MetricValues**

20-5 Triggers Collection

[Get] /redfish/v1/TelemetryService/Triggers

[Post] /redfish/v1/TelemetryService/Triggers

- **Members**
- **Members@odata.count**
- **Name**

POST

Request:

POST https://{{ip}}/redfish/v1/TelemetryService/Triggers
 Content-Type: application/json

The following properties are mandatory to create a trigger:

- **Id**
- **Name**
- **MetricType**
- **TriggerActions**
- **NumericTriggers** or (**DiscreteTriggerCondition & DiscreteTriggers**)
- **MetricProperties**

Note:

- Status->State and Status-Health are read-only attributes and cannot be passed in the POST Request Body.
- Only a maximum of 25 triggers can be created.

Example POST Request to create Numeric Triggers Body:

```
{
  "Id": "Temperature_Trigger",
  "Name": "Temperature_Trigger",
  "MetricType": "Numeric",
  "TriggerActions": [ "LogToLogService" ],
  "NumericTriggers": [ {
    "Name": "UpperThresholdCritical",
    "Value": 50.0,
    "DirectionOfCrossing": "Increasing"
  }, {
    "Name": "UpperThresholdNonCritical",
    "Value": 48.1, "DirectionOfCrossing": "Increasing"
  } ],
  "MetricProperties": [ "/redfish/v1/Chassis/Self/Thermal#/Temperatures/0/ReadingCelsius" ]
}
```

Example POST Request to create Discrete Triggers Body:

```
{
  "Id": "Chassis_LED",
  "Name": "Chassis_LED",
  "MetricType": "Discrete",
  "TriggerActions": [ "LogToLogService", "RedfishEvent" ],
  "DiscreteTriggerCondition": "Specified",
  "DiscreteTriggers": [ {
    "Name": "LED_On",
    "Value": "On", "Severity":
    "Warning"
  } ],
  "MetricProperties": [ "/redfish/v1/Chassis/Self#/IndicatorLED" ]
}
```

20-5-1 Triggers

[Get] /redfish/v1/TelemetryService/Triggers/{instance}

[Delete] /redfish/v1/TelemetryService/Triggers/{instance}

- **Id**

- **Name**

- **MetricType**

- **DiscreteTriggerCondition**

- **Status**

- **DiscreteTriggers**

- **Description**

22. Extension Redfish API

22-1 Chassis (Only for Grace)

[GET] /redfish/v1/Chassis/Baseboard_{instanceId}

[GET] /redfish/v1/Chassis/CPU_{instanceId}

[GET] /redfish/v1/Chassis/ERoT_CPU_{instanceId}

[GET] /redfish/v1/Chassis/ERoT_GPU_{instanceId}

[GET] /redfish/v1/Chassis/FPGA_{instanceId}

[GET] /redfish/v1/Chassis/GPU_{instanceId}

[GET] /redfish/v1/Chassis/ProcessorModule_{instanceId}

- **Actions**

- **Assembly** (for Baseboard_{instanceId}, GPU_{instanceId})

- **AssetTag**

- **ChassisType**

- **HeightMm** (for GPU_{instanceId})

- **Control** (for Baseboard_{instanceId}, ProcessorModule_{instanceId})

- **Id**

- **IndicatorLED**

- **IndicatorLED@Redfish.AllowableValues**

- **Links**

- **ComputerSystems**

- **ComputerSystems@odata.count**

- **Drives**

- **Drives@odata.count**

- **ManagedBy**

- **ManagedBy@odata.count**

- **LogServices** (for ERoT_CPU_{instanceId}, ERoT_GPU_{instanceId})

- **MaxPowerWatts** (for GPU_{instanceId})

- **MinPowerWatts** (for GPU_{instanceId})

- **Name**

- **Oem**

- **Nvidia**

- **Capabilities** (for Baseboard_{instanceId}, FPGA_{instanceId}, GPU_{instanceId})

- **HardwareWriteProtected** (for Baseboard_{instanceId})

- **HardwareWriteProtectedControl** (for Baseboard_{instanceId})

- **WriteProtectionJumper** (for Baseboard_{instanceId})

- **PowerState** (for Baseboard_{instanceId})

- **PCleDevices** (for GPU_{instanceId})

- **PartNumber** (for GPU_{instanceId})

- **PowerState**

- **Sensors**

- **SerialNumber** (for GPU_{instanceId})

- **Status**

- **Health**

- **State**

- **UUID**
- **WidthMm (for GPU_{instanceId})**

22-1-1 Asembly

[GET] /redfish/v1/Chassis/Baseboard_{instanceId}/Assembly

[GET] /redfish/v1/Chassis/GPU_{instanceId}/Assembly

- **Assemblies**
 - **MemberId**
- **Name**
- **Assemblies@odata.count**
- **Id**
- **Name**

22-1-2 Capabilities

[GET] /redfish/v1/Chassis/Baseboard_{instanceId}/Oem/Nvidia/Capabilities

[GET] /redfish/v1/Chassis/FPGA_{instanceId}/Oem/Nvidia/Capabilities

[GET] /redfish/v1/Chassis/GPU_{instanceId}/Oem/Nvidia/Capabilities

- **Capabilities**
 - **DWORD_0**
 - **DWORD_1**
 - **DWORD_2**
 - **DWORD_3**
- **Id**
- **Name**

22-1-3 Controls Collection

[GET] /redfish/v1/Chassis/Baseboard_{instanceId}/Controls

[GET] /redfish/v1/Chassis/ProcessorModule_{instanceId}/Controls

- **Description**
- **Members**
- **Members@odata.count**
- **Name**

22.1.3.1 Controls

[GET] /redfish/v1/Chassis/Baseboard_{instanceId}/Controls/{instance}

[GET] /redfish/v1/Chassis/ProcessorModule_{instanceId}/Controls/{instance}

- **Accuracy**
- **AllowableMax**
- **AllowableMin**
- **Id**
- **Name**
- **Oem**

22. Extension Redfish API

22-1 Chassis (Only for Grace)

[GET] /redfish/v1/Chassis/Baseboard_{instanceId}

[GET] /redfish/v1/Chassis/CPU_{instanceId}

[GET] /redfish/v1/Chassis/ERoT_CPU_{instanceId}

[GET] /redfish/v1/Chassis/ERoT_GPU_{instanceId}

[GET] /redfish/v1/Chassis/FPGA_{instanceId}

[GET] /redfish/v1/Chassis/GPU_{instanceId}

[GET] /redfish/v1/Chassis/ProcessorModule_{instanceId}

- **Actions**

- **Assembly** (for Baseboard_{instanceId}, GPU_{instanceId})

- **AssetTag**

- **ChassisType**

- **HeightMm** (for GPU_{instanceId})

- **Control** (for Baseboard_{instanceId}, ProcessorModule_{instanceId})

- **Id**

- **IndicatorLED**

- **IndicatorLED@Redfish.AllowableValues**

- **Links**

- **ComputerSystems**

- **ComputerSystems@odata.count**

- **Drives**

- **Drives@odata.count**

- **ManagedBy**

- **ManagedBy@odata.count**

- **LogServices** (for ERoT_CPU_{instanceId}, ERoT_GPU_{instanceId})

- **MaxPowerWatts** (for GPU_{instanceId})

- **MinPowerWatts** (for GPU_{instanceId})

- **Name**

- **Oem**

- **Nvidia**

- **Capabilities** (for Baseboard_{instanceId}, FPGA_{instanceId}, GPU_{instanceId})

- **HardwareWriteProtected** (for Baseboard_{instanceId})

- **HardwareWriteProtectedControl** (for Baseboard_{instanceId})

- **WriteProtectionJumper** (for Baseboard_{instanceId})

- **PowerState** (for Baseboard_{instanceId})

- **PCleDevices** (for GPU_{instanceId})

- **PartNumber** (for GPU_{instanceId})

- **PowerState**

- **Sensors**

- **SerialNumber** (for GPU_{instanceId})

- **Status**

- **Health**

- **State**

- **UUID**
- **WidthMm (for GPU_{instanceId})**

22-1-1 Asembly

[GET] /redfish/v1/Chassis/Baseboard_{instanceId}/Assembly

[GET] /redfish/v1/Chassis/GPU_{instanceId}/Assembly

- **Assemblies**
 - **MemberId**
- **Name**
- **Assemblies@odata.count**
- **Id**
- **Name**

22-1-2 Capabilities

[GET] /redfish/v1/Chassis/Baseboard_{instanceId}/Oem/Nvidia/Capabilities

[GET] /redfish/v1/Chassis/FPGA_{instanceId}/Oem/Nvidia/Capabilities

[GET] /redfish/v1/Chassis/GPU_{instanceId}/Oem/Nvidia/Capabilities

- **Capabilities**
 - **DWORD_0**
 - **DWORD_1**
 - **DWORD_2**
 - **DWORD_3**
- **Id**
- **Name**

22-1-3 Controls Collection

[GET] /redfish/v1/Chassis/Baseboard_{instanceId}/Controls

[GET] /redfish/v1/Chassis/ProcessorModule_{instanceId}/Controls

- **Description**
- **Members**
- **Members@odata.count**
- **Name**

22.1.3.1 Controls

[GET] /redfish/v1/Chassis/Baseboard_{instanceId}/Controls/{instance}

[GET] /redfish/v1/Chassis/ProcessorModule_{instanceId}/Controls/{instance}

- **Accuracy**
- **AllowableMax**
- **AllowableMin**
- **Id**
- **Name**
- **Oem**

22-1-4 LogServices Collection

[GET] /redfish/v1/Chassis/ERoT_CPU_{instanceId}/LogServices

[GET] /redfish/v1/Chassis/ERoT_GPU_{instanceId}/LogServices

- **Description**
- **Members**
- **Members@odata.count**
- **Name**

22.1.4.1 LogServices

[GET] /redfish/v1/Chassis/ERoT_CPU_{instanceId}/LogServices/DebugTokenService

[GET] /redfish/v1/Chassis/ERoT_GPU_{instanceId}/LogServices/DebugTokenService

[POST] /redfish/v1/Chassis/ERoT_CPU_{instanceId}/LogServices/DebugTokenService/Actions/LogService.CollectDiagnosticData

[POST] /redfish/v1/Chassis/ERoT_GPU_{instanceId}/LogServices/DebugTokenService/Actions/LogService.CollectDiagnosticData

- **Actions**
- **DateTime**
- **DateTimeLocalOffset**
- **Description**
- **Entries**
- **Id**
- **LogEntryType**
- **MaxNumberOfRecords**
- **Name**
- **OverWritePolicy**
- **ServiceEnabled**
- **Status**

POST

Request:

POST

https://{{ip}}/redfish/v1/Chassis/ERoT_CPU_{instanceId}/LogServices/DebugTokenService/Actions/LogService.CollectDiagnosticData

Content-Type: application/json

POST

https://{{ip}}/redfish/v1/Chassis/ERoT_GPU_{instanceId}/LogServices/DebugTokenService/Actions/LogService.CollectDiagnosticData

Content-Type: application/json

Example POST Request Body:

```
{
  "DiagnosticDataType": "OEM",
  "OEMDiagnosticDataType": "GetDOTSignTestToken"
}
```

22.1.4.1.1 Entries Collection

[GET] /redfish/v1/Chassis/ERoT_CPU_{instanceId}/LogServices/DebugTokenService/Entries

[GET] /redfish/v1/Chassis/ERoT_GPU_{instanceId}/LogServices/DebugTokenService/Entries

- **Description**
- **Members**
- **Members@odata.count**
- **Name**

22.1.4.1.1.1 Entries

[GET] /redfish/v1/Chassis/ERoT_CPU_{instanceId}/LogServices/DebugTokenService/Entries/{instance}

[GET] /redfish/v1/Chassis/ERoT_GPU_{instanceId}/LogServices/DebugTokenService/Entries/{instance}

- **AdditionalDataSizeBytes**
- **AdditionalDataURI**
- **Created**
- **Description**
- **DiagnosticDataType**
- **EntryCode**
- **EntryType**
- **EventTimestamp**
- **EventType**
- **Id**
- **Name**
- **Severity**

22-1-5 PCIe Devices Collection

[GET] /redfish/v1/Chassis/GPU_{instanceId}/PCleDevices

- **Description**
- **Members**
- **Members@odata.count**
- **Name**

22.1.5.1 PCIe Devices

[GET] /redfish/v1/Chassis/GPU_{instanceId}/PCleDevices/{instance}

- **DeviceType**
- **Id**
- **Manufacturer**
- **Model**
- **Name**
- **PCIeInterface**

22-1-6 Sensor Collection

[GET] /redfish/v1/Chassis/Baseboard_{instanceId}/Sensors
[GET] /redfish/v1/Chassis/CPU_{instanceId}/Sensors
[GET] /redfish/v1/Chassis/ERoT_CPU_{instanceId}/Sensors
[GET] /redfish/v1/Chassis/ERoT_GPU_{instanceId}/Sensors
[GET] /redfish/v1/Chassis/FPGA_{instanceId}/Sensors
[GET] /redfish/v1/Chassis/GPU_{instanceId}/Sensors
[GET] /redfish/v1/Chassis/ProcessorModule_{instanceId}/Sensors

- **Description**
- **Members**
- **Members@odata.count**
- **Name**

22.1.6.1 Sensor

[GET] /redfish/v1/Chassis/Baseboard_{instanceId}/Sensors/{instance}
[GET] /redfish/v1/Chassis/CPU_{instanceId}/Sensors/{instance}
[GET] /redfish/v1/Chassis/ERoT_CPU_{instanceId}/Sensors/{instance}
[GET] /redfish/v1/Chassis/ERoT_GPU_{instanceId}/Sensors/{instance}
[GET] /redfish/v1/Chassis/FPGA_{instanceId}/Sensors/{instance}
[GET] /redfish/v1/Chassis/GPU_{instanceId}/Sensors/{instance}
[GET] /redfish/v1/Chassis/ProcessorModule_{instanceId}/Sensors/{instance}

- **Accuracy**
- **Id**
- **Implementation**
- **Name**
- **Oem**
- **Reading**
- **ReadingRangeMax**
- **ReadingRangeMin**
- **ReadingType**
- **ReadingUnits**
- **SensingInterval**
- **Status**

22-2 System (Only for Grace)

22-2-1 Memory

[GET] /redfish/v1/Systems/{instance}/Memory/GPU_{instanceId}_DRAM_{instanceId}

- **AllowedSpeedsMHz**
- **EnvironmentMetrics**
- **Id**
- **Links**
- **MemoryDeviceType**
- **MemoryType**
- **Metrics**
- **Oem**
- **OperatingSpeedMhz**
- **PartNumber**
- **Status**

22.2.1.1. EnvironmentMetrics

[GET] /redfish/v1/Systems/{instance}/Memory/GPU_{instanceId}_DRAM_{instanceId}/

EnvironmentMetrics

- **Description**
- **Id**
- **Name**
- **Oem**
- **PowerLimitWatts**
- **TemperatureCelsius**

22.2.1.2. MemoryMetrics

[GET] /redfish/v1/Systems/{instance}/Memory/GPU_{instanceId}_DRAM_{instanceId}/

MemoryMetrics

- **CapacityUtilizationPercent**
- **Id**
- **LifeTime**
- **Name**
- **Oem**
- **OperatingSpeedMHz**

22-2-2 Processor

[GET] /redfish/v1/Systems/{instance}/Processors/FPGA_{instanceId}

- **FPGA**
- **FirmwareVersion**
- **Id**
- **Links**
- **Manufacturer**
- **MemorySummary**
- **Name**
- **Ports**
- **ProcessorType**
- **Status**

[GET] /redfish/v1/Systems/{instance}/Processors/GPU_{instanceId}

- **Action**
- **EnvironmentMetrics**
- **FirmwareVersion**
- **Id**
- **Links**
- **Manufacturer**
- **MaxSpeedMHz**
- **MemorySummary**
- **ECCModeEnabled**
- **Metrics**
- **Metrics**
- **MinSpeedMHz**
- **Model**
- **Name**
- **Oem**
- **OperatingSpeedMHz**
- **PartNumber**
- **ProcessorType**
- **SerialNumber**
- **SpeedLimitMHz**
- **SpeedLocked**
- **Status**
- **SystemInterface**
- **UUID**
- **Version**

22.2.2.1. EnvironmentMetrics

[GET] /redfish/v1/Systems/{instance}/Processors/GPU_{instanceId}/EnvironmentMetrics

- **Description**
- **Id**
- **Name**

- **Oem**
- **PowerLimitWatts**
- **TemperatureCelsius**

22.2.2.2. **MemoryMetrics**

[GET] /redfish/v1/Systems/{instance}/Processors/GPU_{instanceId}/MemorySummary/
MemoryMetrics

- **Id**
- **LifeTime**
- **Name**
- **OperatingSpeedMHz**

22.2.2.3. **Port Collection**

[GET] /redfish/v1/Systems/{instance}/Processors/FPGA_{instanceId}/Ports

- **Description**
- **Members**
- **Members@odata.count**
- **Name**

22.2.2.3.1. **Ports**

[GET] /redfish/v1/Systems/{instance}/Processors/FPGA_{instanceId}/Ports/{instance}

- **ActiveWidth**
- **CurrentSpeedGbps**
- **Id**
- **Metrics**
- **Name**

22.2.2.3.1.1. **Metrics**

[GET] /redfish/v1/Systems/{instance}/Processors/FPGA_{instanceId}/Ports/{instance}/Metrics

- **Id**
- **Name**
- **PCIEErrors**

22.2.2.4. **ProcessorMetrics**

[GET] /redfish/v1/Systems/{instance}/Processors/GPU_{instanceId}/ProcessorMetrics - **Id**

- **BandwidthPercent**
- **CacheMetricsTotal**
- **CoreVoltage**
- **Id**
- **Name**
- **Oem**
- **OperatingSpeedMHz**
- **PCIEErrors**

22-3 UpdateService (Only for Grace)

22-3-1 FirmwareInventory

[GET] /redfish/v1/UpdateService/FirmwareInventory /CPU_{instanceId}

[GET] /redfish/v1/UpdateService/FirmwareInventory /ERoT_CPU_{instanceId}

[GET] /redfish/v1/UpdateService/FirmwareInventory /ERoT_GPU_{instanceId}

[GET] /redfish/v1/UpdateService/FirmwareInventory /FPGA_{instanceId}

[GET] /redfish/v1/UpdateService/FirmwareInventory /FW_GPU_{instanceId}

[GET] /redfish/v1/UpdateService/FirmwareInventory /InfoROM_GPU_{instanceId}

- **Id**

- **Manufacturer** (for *ERoT_CPU_{instanceId}*, *ERoT_GPU_{instanceId}*, *FPGA_{instanceId}*, *FW_GPU_{instanceId}*)

- **Name**

- **Updateable** (for *FPGA_{instanceId}*)

- **Version**

- **WriteProtected**

22-3-2 SoftwareInventory

[GET] /redfish/v1/UpdateService/SoftwareInventory/Driver_GPU_{instanceId}

- **Id**

- **Name**

- **Status**

- **Health**

- **State**